



Access Unit

Access Control



Configuration Manual

Firmware: 2.30
Version: 2.30

www.2n.cz

The 2N TELEKOMUNIKACE a.s. is a Czech manufacturer and supplier of telecommunications equipment.



The product family developed by 2N TELEKOMUNIKACE a.s. includes GSM gateways, private branch exchanges (PBX), and door and lift communicators. 2N TELEKOMUNIKACE a.s. has been ranked among the Czech top companies for years and represented a symbol of stability and prosperity on the telecommunications market for almost two decades. At present, we export our products into over 120 countries worldwide and have exclusive distributors on all continents.



2N[®] is a registered trademark of 2N TELEKOMUNIKACE a.s. Any product and/or other names mentioned herein are registered trademarks and/or trademarks or brands protected by law.



2N TELEKOMUNIKACE a.s. administers the FAQ database to help you quickly find information and to answer your questions about 2N products and services. On www.faq.2n.cz you can find information regarding products adjustment and instructions for optimum use and procedures „What to do if...”.



2N TELEKOMUNIKACE a.s. hereby declares that the 2N product complies with all basic requirements and other relevant provisions of the 1999/5/EC directive. For the full wording of the Declaration of Conformity see the CD-ROM (if enclosed) or our website at www.2n.cz.



The 2N TELEKOMUNIKACE a.s. is the holder of the ISO 9001:2009 certificate. All development, production and distribution processes of the company are managed by this standard and guarantee a high quality, technical level and professional aspect of all our products.

Content:

- 1. Product Overview
- 2. Express Wizard for Basic Settings
- 3. Function Licensing
- 4. Signalling of Operational Statuses
- 5. Web Interface Configuration
 - 5.1 Status
 - 5.2 Directory
 - 5.3 Hardware
 - 5.4 Services
 - 5.5 System
- 6. Supplementary Information
 - 6.1 Troubleshooting
 - 6.2 Directives, Laws and Regulations
 - 6.3 General Instructions and Cautions

1. Product Overview

Door access system **2N Access Unit** can (with addon software and/or with **2N IP intercoms**) offers you a whole setup for access control over any whole object.

Your **2N Access Unit** can be equipped with a numeric keypad, so you can use it as code lock.

Your **2N Access Unit** can also be equipped with another RFID card reader, so it can be used as a part of your security system or attendance system in your company.

2N Access Unit can be equipped with a relay to control electric lock or any other device connected to this access system. There are a lot of possibilities to set up, when and how to activate these switches - with code, automatically, by pressing a button etc.

The following symbols and pictograms are used in the manual:

Safety

- Always abide by this information to prevent persons from injury.

Warning

- Always abide by this information to prevent damage to the device.

Caution

- Important information for system functionality.

 Tip

- Useful information for quick and efficient functionality.

 Note

- Routines or advice for efficient use of the device.

2. Express Wizard for Basic Settings

LAN Connection Setting

You have to know the IP address to connect to the **2N Access Unit** configuration interface successfully. Automatic IP address retrieval from the DHCP server is set by default in the **2N Access Unit**. Thus, if connected to a network in which a DHCP server configured to assign IP addresses to all new devices is available, the **device** will obtain an IP address from the DHCP server. The **2N Access Unit** IP address can be found in the DHCP server status (according to the MAC address given on the production plate), or will be communicated to you by the **2N Access Unit** voice function; refer to the Installation Manual.

If there is no DHCP server in your LAN, use the **2N Access Unit** RESET button to set the static IP address mode; refer to the respective Installation Manual. Your unit address will then be **192.168.1.100**. Use it for the first login and then change it if necessary.

Now enter the IP address into your favourite browser. We recommend you to use the latest Chrome, Firefox or Internet Explorer (Edge) versions as **2N Access Unit** is not fully compatible with earlier browser versions.

Use the name "admin" and password "2n" (i.e. default reset password) for your first login to the configuration interface. We recommend you to change the default password upon your first login; refer to the Password parameter in the **Services / Web Server** menu. Remember the password well or put it down. It is because if you forget the password, you will have to reset the intercom to default values (refer to the respective Installation Manual) thus losing all your current configuration changes.



- FAQ: IP address – How to get the 2N Access Unit IP address?

Firmware Update

We also recommend you to update your firmware upon the first login to the **device**. Refer to **www.2n.cz** for the latest firmware version. Press the **Update Firmware** button in the **System/Maintenance** menu to upload firmware. The device will get restarted upon upload and only then the updating process will be complete. The process takes about 1 minute.

Electric Lock Switching Settings

An electric door lock can be attached to the **2N Access Unit** and controlled by a code from the numeric keypad. Connect the electric lock as instructed in the respective Installation Manual.

Switch 1

Switch 2

☒ Switch Enabled

Basic Settings ▾

Switch Mode

Monostable ▾

Switch-On Duration

5 [s]

Controlled Output

Relay 1 ▾

Output Type

Normal ▾

Time Profile

☒ [not used] ▾
 ☐ 

Test the switch

Activation Codes ▾

	CODE	TIME PROFILE
1	00	☒ [not used] ▾ ☐ 
2		☒ [not used] ▾ ☐ 

Distinguish on/off codes ☐

Enable the switch in the Switch Enabled parameter on the **Hardware / Switches / Switch 1** tab, set the Controlled Output to the intercom output to which the electric door lock is connected. Now set one or more activation codes for the electric door lock switching.

3. Function Licensing

2N Access Unit only supports two licensed functions: 2N Access Unit Lift module license and 2N Access Unit - NFC license. The NFC license can only be used for the **2N Access Unit** version that is equipped with a 13MHz card reader.

Part No.	License Name
916012	2N Access Unit NFC license
9160401	2N Access Unit Lift module license

Info

- Activate the 800-hour license trial versions via the web interface in the System / Licenses section.

License	Features	2N® IP Verso	2N® LTE Verso	2N® IP Solo	2N® IP Base	2N® IP Force	2N® IP Safety	2N® IP Vario	2N® IP Vario s displejem	2
Enhanced Audio (included in Gold)	User sounds	★	★	★	★	★	★	★	✓	
	Automatic audio test	★	★	★	★	★	★	★	✓	
	Noise detection	★	★	★	★	★	★	★	✓	
Enhanced Video (included in Gold)	Audio/video streaming (RTSP Server)	★	★*	★	★	★	★	★	✓	
	External camera support	★	★*	★	★	★	★	★	✓	
	ONVIF support	★	★*	★	★	★	★	★	✓	
	PTZ support	★	★	★	★	★	★	★	✓	
	Motion detection support	★	★	★	★	★	★	★	✓	
	Advanced switch setting options	★	★	★	★	★	★	★	✓	
	HTTP API	★	★*	★	★	★	★	★	✓	
Enhanced Integration (included in Gold)	Automation function	★	★	★	★	★	★	★	✓	
	E-mail sending (SMTP client)	★	★	★	★	★	★	★	✓	
	Automatic update (TFTP/HTTP client)	★	★	★	★	★	★	★	✓	
	FTP client	★	★	★	★	★	★	★	✓	
	SNMP client	★	★*	★	★	★	★	★	✓	
	TR-069	★	★	★	★	★	★	★	✓	
	Synergis	★	★*	★	★	★	★	★	✓	
	802.1x support	★	✗	★	★	★	★	★	✓	
	SIPS (TLS) support	★	★	★	★	★	★	★	✓	
Enhanced Security (included in Gold)	Switch Blocking by Tamper	★	★	★	★	★	★	★	✓	
	SRTP support	★	★	★	★	★	★	★	✓	
	Silent alarm	★	★	★	★	★	★	★	✓	
	Limit unsuccessful access attempts	★	★	★	★	★	★	★	✓	
	Anti-Passback	★	★	✗	★	★	✗	★	✓	
	Scrambled keypad	★	★	✗	✗	✗	✗	✗	✗	
	NFC support	★	★	✗	★	★	✗	✗	✗	
	NFC (included in Gold)	★	★	✗	★	★	✗	✗	✗	
InformaCast	InformaCast support	★	★*	★	★	★	★	★	★	
Lift Module	Lift Control	★	✗	✗	✗	★	★	★	★	



– factory value

★ – licensed function to be purchased additionally

✗ – unavailable

*) The service availability depends on the mobile provider's network configuration.



**) The scrambled keypad function is only available for 2N Access Unit 2.0.

4. Signalling of Operational Statuses

2N Access Unit generates sounds to signal changes and switching of operational statuses. Each status change is assigned a different type of tone. See the table below for the list of signals:

Note

- *Signalling of some of the above mentioned statuses can be modified; refer to the User Sounds subsection.*

Tones	Meaning
	User activated This tone signals entering of the user activation code. The activation code is used for user (user's position) activation. Refer to the Users subsection for the activation code settings.
	User deactivated This tone signals entering of the user deactivation code. The deactivation code is used for user (user's position) deactivation. Refer to the Users subsection for the deactivation code settings.
	Profile activated This tone signals profile activation. This function helps enable alerting of a user group in an office, for example. Refer to the Profile subsection for the activation code settings.
	Profile deactivated This tone signals profile deactivation. Refer to the Profile subsection for the deactivation code settings.

	Internal application launched The internal application of the 2N Access Unit is launched upon the 2N Access Unit power up or restart. A successful launch is signaled by this tone combination.
	Connected to LAN, IP address received 2N® Access Unit logs in upon the internal application launch. A successful LAN login is signalled by this tone combination.
	Disconnected from LAN, IP address lost This tone combination signals UTP cable disconnection from the 2N Access Unit.
	Default reset of network parameters Upon power up, a 30 s timeout is set for the default reset code entering. Refer to the Device Configuration subsection in the 2N Access Unit Installation Manual for details.

5. Web Interface Configuration



Start Screen

The start screen is an introductory overview screen displayed upon login to the **2N Access Unit** web interface. Use the  button in the left-hand upper corner of the following web interface pages to return to this screen anytime.

The screen header includes the **2N Access Unit** name (refer to the Display Name parameter in the **Services / Web Server/ Basic Settings**). Select the web interface language with the **CZ, EN, DE, FR, IT, ES and RU** buttons. Press the Log out button in the right-hand upper corner to log out.

The start screen is also the first menu level and quick navigation (click on a tile) to selected intercom configuration sections. Some tiles also display the state of selected services.

Configuration Menu

The 2N Access Unit configuration includes 5 main menus: **Status**, **Directory**, **Hardware**, **Services** and **System** including submenus; refer to the survey below.

Status

- **Device** – essentials on the 2N Access Unit
- **Services** – information on active services and their states
- **Licence** – current states of licences and available 2N Access Unit functions
- **Access Log** – list of last ten access cards
- **Events** – list of events

Directory

- **Users** – settings for user phone numbers, quick dial buttons, access cards and switch control user codes
- **Time Profiles** – time profile settings
- **Holidays** – holiday settings

Hardware

- **Switches** – electric lock, lighting, etc. settings
- **Audio** – audio, signalling tone, etc. volume settings
- **Keyboard** – keyboard and code input settings
- **Backlight** – intensity of backlight
- **Card Reader** – card reader, Wiegand interface settings
- **Digital Inputs** – management of digital inputs
- **Extenders** – 2N Access Unit extender settings

Services

- **E-mail** – sending e-mails when e.g. denied events
- **Mobile Key** – Bluetooth settings and management of paired devices
- **Automation** – flexible intercom settings according to user requirements
- **HTTP API** – application programming interface for controlling selected functions of intercom
- **Web server** – web server and access password settings
- **SNMP** – functionality enabling remote monitoring of intercoms in the network using SNMP protokol

System


- **Network** – LAN connection settings, 802.1x, packet capturing
- **Date and time** – real time and time zone settings
- **Licence** – licence settings, trial licence activation
- **Certificates** – certificate and private key settings
- **Auto Provisioning** – automatic firmware and configuration update settings
- **Syslog** – syslog message sending settings
- **Maintenance** – backup and configuration reset, firmware update
- **5.1 Status**
- **5.2 Directory**
- **5.3 Hardware**
- **5.4 Services**
- **5.5 System**



Caution

In order to ensure the full functioning and guaranteed outputs we strongly recommend a verification of the timeliness of version of product or facility already during the installation process. The customer takes into consideration that the product or facility can achieve the guaranteed outputs and be fully operational pursuant to the producer's instructions only by using the most recent version of product or facility, which has been tested for full interoperability and has not been determined by the producer as incompatible with certain versions of other products, only in conformity with the producer's instructions, guidelines, manual or recommendation and only in conjunction with suitable products and facilities of the other producers. The most recent versions are available on the website https://www.2n.cz/cs_CZ/, or specific facilities, depending on their technical capacity, allow updating in the configuration interface. Should the customer use any other version of product or facility than the most recent one, or the version that has been determined by the producer as incompatible with certain versions of other producers' products or facilities, or the product or facility in a way incompatible with the producer's instructions, guidelines, manual or recommendation or in conjunction with unsuitable products or facilities of the other producers, he or she is aware of all potential limitations of functionality of such a product or facility and all relating consequences. Should the customer use any other than the most recent version of the product or facility, or the version that has been determined by the producer as incompatible with certain versions of other producers' products or facilities, or the product or facility in a way incompatible with the producer's instructions, guidelines, manual or recommendation or in conjunction with unsuitable products or facilities of the other producers, he or she agrees that the company 2N TELEKOMUNIKACE a. s. is not liable neither for any limitation of such a product's functionality, nor for any damage, loss or injury relating to such a potential limitation of functionality.

5.1 Status



The **Status** menu provides clear status and other essential information on the **2N Access Unit**. The menu is divided into the following tabs:

Device

This tab displays basic information on the device model, its features, firmware and bootloader versions and so on.

Device Info ▾

Product Name **2N Access Unit**
 Hardware Version **586v2**
 Serial Number **54-1105-0190**
 Firmware Version **2.28.0.37.1**
 Bootloader Version **2.10.0.19.3**
 Up Time **1h 10m 44s**
 Factory Certificate Installed **No**

[Locate Device](#)

Device Features ▾

Card Reader **YES**
 Card Reader Type **125 kHz**
 Module Count **0**
 Signaling LEDs **YES**
 Audio Hardware **N/A**

Services

This tab displays the statuses of the network interface and selected services.

Network Interface Status ▾

MAC Address **7C-1E-B3-01-1F-F6**
 DHCP Status **USED**
 IP Address **10.0.27.46**
 Network Mask **255.255.255.0**
 Default Gateway **10.0.27.1**
 Primary DNS **10.0.100.102**
 Secondary DNS **10.0.100.5**

Licence

This tab displays the list of licensed functions of the **2N Access Unit** including their current availability (on the basis of a valid licence key entered in the **System / Licences** menu).

Licensed Features ▾	
Automatic Updates	YES
Advanced Switch Settings	YES
HTTP API	YES
SMTP Service	YES
802.1x Authentication	YES
Automation	YES
FTP Client	YES
NFC Support	YES
SNMP Support	YES
TR069	YES
Switch Blocking by Tamper	YES
Genetec Synergis	YES
Lift Control	YES

Access Log

The **Access Log** tab displays the last 10 records on the cards applied. Each record includes the card tapping time, card ID and type and description details (validity, card owner, etc.).

Access Log ▾

	TIME	CARD ID	CARD TYPE	DESCRIPTION
1	01/01/1970 01:26:12	E012FFF8010BE07F	HID iClass	Access denied
2	01/01/1970 01:26:02	4BCFDC13	MIFARE Classic 1k	Access denied
3	01/01/1970 01:25:59	2B2AB69E	MIFARE Classic 4k	Access denied
4	01/01/1970 01:25:56	802C3202239704	MIFARE Ultralight C	Access denied
5	01/01/1970 01:25:51	802AE19A2E9204	MIFARE DESFire	Access denied
6				
7				
8				
9				
10				

Events

This tab displays activity of the device (switches, signalling leds, pressed keys on keypad etc.). It also allows filtering between events through the 13 optional parameters.



TIME	EVENT TYPE	DESCRIPTION
10 Feb 11:00:09	SwitchStateChanged	switch=1, state=false
10 Feb 11:00:09	MotionDetected	state=out
10 Feb 11:00:06	MotionDetected	state=in
10 Feb 11:00:04	KeyReleased	key=#
10 Feb 11:00:04	SwitchStateChanged	ap=0, session=2, switch=1, state=true, originator=ap
10 Feb 11:00:04	AccessTaken	ap=0, session=2, apbBroken=false
10 Feb 11:00:04	UserAuthenticated	ap=0, session=2, name=Amanda Kheel, uuid=0e6b3
10 Feb 11:00:04	CodeEntered	ap=0, session=2, direction=in, code=582413, type=use
10 Feb 11:00:04	KeyPressed	key=#
10 Feb 11:00:03	KeyReleased	key=3
10 Feb 11:00:03	KeyPressed	key=3
10 Feb 11:00:03	KeyReleased	key=1
10 Feb 11:00:03	KeyPressed	key=1
10 Feb 11:00:02	KeyReleased	key=4
10 Feb 11:00:02	KeyPressed	key=4
10 Feb 11:00:02	KeyReleased	key=2
10 Feb 11:00:02	KeyPressed	key=2
10 Feb 11:00:01	KeyReleased	key=8
10 Feb 11:00:01	KeyPressed	key=8

-  - press the button to export all recorded events to a CSV file.

5.2 Directory

Here is what you can find in this section:

- 5.2.1 Users
- 5.2.2 Time Profiles
- 5.2.3 Holidays

5.2.1 Users



The Users list is one of the crucial parts of the intercom configuration. It contains user information relevant for such intercom functions as quick dialling, RFID card/code door unlocking, missed call e-mails and so on.

The User list contains up to 10 000 users – typically, each user is assigned just one position. The User list provides information on the users that are granted access to the building via the RFID cards.

If your external card reader is connected to the intercom via the Wiegand interface, the card ID is shortened to 6 or 8 characters for transmission (depending on the transmission parameters). If you apply a card to the reader, you will receive a complete ID, which is typically longer (8 chars or more). The last 6 or 8 characters, however, are identical. This is useful for comparing card IDs with the intercom database: if the IDs to be compared have different lengths, they are compared from the end and match has to be found in 6 characters at least. If they have identical lengths, all the characters are compared. This ensures mutual compatibility of the internal and external readers.

All cards applied via the reader or the Wiegand interface are recorded. Refer to the **Status / Access Log** menu for the last 10 cards including the card ID/type, card tapping time and other information if necessary. With small systems, you can make a trick to enter card IDs: tap the card on the intercom reader and find it in the **Access Log**. Double-click to select the card ID and push CTRL+C. Now that you have the card ID in your box, you can insert it with CTRL+V in any intercom setting field.

Having been read, the card ID is compared with the intercom card database. If the card ID matches any of the cards in the database, the appropriate action will be executed: switch activation (door unlocking, etc.). To change the switch number to be

activated, use the **Associated Switch** parameter in the **Hardware / Card Reader** menu or the **Associated Switch** parameter in the **Hardware / Modules** menu of the card reader module.




Search

☐	Name	Accesses
☐	Bobbi	 > 
☐	Indoor talk	   > 
☐	Keith	 > 

15 ▾ 1 - 3 (Total 3)

1

The Search in directory function works as a fulltext search in user names, phone numbers and e-mail addresses. It searches for all matches in the list. Click



to create a new user and



to show the user details. Click



to set the table column display; the default table setting displays the user name, e-mail and assigned accesses. Press



to remove a user and delete its details. The



icons in the access column describe the active user authentications.

Every record in the Users list includes the following parameters:

User Basic Information ▾

Name

E-mail

- **Name** – a mandatory parameter for easier user search, for example.

- **E-mail** – user e-mail address for sending missed call information. You can enter more e-mail addresses separated with commas.

Access Settings ▾

Entry Rules

Access Enabled ☒

Access Profiles ☒ [not used] ▾ ☐

Exit Rules

Access Enabled ☒

Access Profiles ☒ [not used] ▾ ☐

Validity term

Valid from

Valid to

- **Entry Rules**
 - **Access Enabled** – enable authentication via this access point.
 - **Access Profiles** – select one of the profiles pre-defined in Directory / Time profiles or set the time profile for this element manually.
- **Exit Rules**
 - **Access Enabled** – enable authentication via this access point.
 - **Access Profiles** – select one of the profiles pre-defined in Directory / Time profiles or set the time profile for this element manually.
- **Validity term**
 - **Valid from** – set the beginning of the mode validity term.
 - **Valid to** – set the end of the mode validity term.

User Codes ▾

PIN Code

Switch Codes

Switch 1

Switch 2

Each user can be assigned a private switch activation code. The user switch codes can be arbitrarily combined with the universal switch codes defined in the **Hardware | Switches** menu. If the codes are identical with the codes already defined in the intercom configuration, the



mark will appear at the colliding codes.


PIN Code – set the user's Personal Identification Number. The code must include 2 characters at least.

Switch1-2 – set a private user switch activation code: up to 16 characters including digits 0-9 only. The code must include at least two door unlocking characters via the intercom keypad and at least one door unlocking character via DTMF.



Each of the intercom users can be assigned two access RFID card.

- **Card ID** – set the user access card ID: 6-32 characters including 0-9, A-F. Each user can be assigned up to two access cards. When a valid card is tapped on the reader, the switch associated with the card reader gets activated. If the double authentication mode is enabled, the switch can only be activated using both a card and numeric code.
- **Virtual card ID** – set the user virtual card ID for user identification in the devices that are integrated with the **2N IP intercoms** via a Wiegand interface. Each user can be assigned just one virtual card. The virtual card ID is a sequence of 6-32 characters: 0-9, A-F. After the user is validated via the Bluetooth/biometric reader, the identifier is sent to the device integrated with the **2N IP intercom** via Wiegand.



- **Floors** – select the floors available to the user.
- **Time Profile** – select one or more time profiles to be applied. Set the time profiles in the Directory / Time Profiles section.



mark the selection from predefined profiles or manual setting of a time profile for the given element.



set a time profile for the given element.

User Mobile Key  ▾

Auth ID





Pairing State **Inactive**


Pairing valid until **N/A**

- **Auth ID** – set a unique mobile device/user identifier. The parameter value is automatically generated for pairing. You can move Auth ID to another user or copy it to another device in the same location.
 -  pair via USB reader
 -  pair via this device
 -  delete Auth ID
- **Pairing state** – display the current pairing state (Inactive, Waiting for pairing, PIN validity expired or Paired).
- **Pairing valid until** – display the date and time of the generated authorisation PIN validity end.

Pairing via Bluetooth Module in Intercom

To pair a mobile phone with the user:

- Click  at Auth ID to start pairing for the selected user account.
- A dialogue window with the PIN code is displayed.
- Find the appropriate reader in the **2N[®] Mobile Key** application and press Start pairing.
- Enter the code from item 2 into the input field.
- Pairing is completed.



- **User Fingerprints** – display the set count of fingerprints; up to 2 different fingerprints can be set. This section is displayed only if the biometric reader module is available.
 -  enrol via USB reader
 -  enrol via Fingerprint scanner module 3

Caution

- The fingerprint loading capacity is up to 2000 per device.


User Fingerprint Setting Instructions

To load fingerprints, use the 2N[®] Access Unit Fingerprint reader (Part No. 916019) or an external USB fingerprint scanner (Part No. 9137423E) as follows:


1a) To load fingerprints via the 2N[®] Access Unit Fingerprint reader, use the web interface at the selected user and click  Load via fingerprint reader module in Directory / Users/ User fingerprints.



1b) To load fingerprints via an external USB fingerprint scanner, use the 2N[®] IP USB Driver and select Fingerprint reader in the Settings and press OK for confirmation. Click  Load via fingerprint reader module in Directory / Users/ User fingerprints via the web interface at the selected user.




2) Click to select a finger for fingerprint loading.




Up to two fingerprints may be saved for each user.


3) Click SCAN FINGER to load a fingerprint.




4) Place the selected finger on an external USB reader. This process is repeated three times for greater precision.



Repeat the process if any inconsistency occurs during fingerprint reading.



5) If fingerprint scanning is successful, click DONE to confirm the settings.




To set the finger function, click the




icon to display the list of available functions:


- Door opening
- Silent alarm; configurable only if Door opening is active
- Automation F1 - generate the FingerEntered event in Automation. F1 helps distinguish the applied finger in Automation.
- Automation F2 - generate the FingerEntered event in Automation. F2 helps distinguish the applied finger in Automation.



Click SAVE AND QUIT to confirm the fingerprint enrolment and selected functions.




6) You can check the current settings in the User tab.




USB RFID Card Reader

It is possible to read the card ID via an RFID card reader. Proceed as follows:

- Go to the 2N[®] USB Driver settings.




- Set up the COM port for the connected reader.




- Press the Read button via the 2N Access Unit web interface.



- Tap the card on the card reader.



- The card ID is successfully read.



Do not forget to save the configuration.

5.2.2 Time Profiles



Such **2N Access Unit** functions as RFID card/numeric code access, for example, can be time-limited by being assigned a **time profile**. By assigning a time profile you can:

- block all calls to a selected user beyond the set time interval
- block calls to selected user phone numbers beyond the set time interval
- block RFID access for a user beyond the set time interval
- block numeric code access for a user beyond the set time interval
- block switch activation beyond the set time interval

Assign a time profile according to a week time sheet to define availability of the selected function. Just set from-to and/or days in the week on which the function shall be available. **2N Access Unit** helps you create up to 20 time profiles that can be assigned to the function; refer to the Users, Access Cards and Switches settings.

The time profiles can be defined not only using the week time sheet but also manually with the aid of special activation/deactivation codes. Enter the activation/deactivation codes using the numeric keypad of your **2N Access Unit** to activate/deactivate a function after arriving in/before leaving your office, for example.

Refer to the **Directory / Time Profiles** menu for the time profile settings.

List of Parameters



- **Profile Name** – enter a profile name. This parameter is optional and helps you find items in the time profile list in the switch, card and phone number settings more easily.

Profile Time Sheet ▾

Sunday	00 01 02 03 04 05 06 07 08 09 10 11 12 13 14 15 16 17 18 19 20 21 22 23 24
Monday	00 01 02 03 04 05 06 07 08 09 10 11 12 13 14 15 16 17 18 19 20 21 22 23 24
Tuesday	00 01 02 03 04 05 06 07 08 09 10 11 12 13 14 15 16 17 18 19 20 21 22 23 24
Wednesday	00 01 02 03 04 05 06 07 08 09 10 11 12 13 14 15 16 17 18 19 20 21 22 23 24
Thursday	00 01 02 03 04 05 06 07 08 09 10 11 12 13 14 15 16 17 18 19 20 21 22 23 24
Friday	00 01 02 03 04 05 06 07 08 09 10 11 12 13 14 15 16 17 18 19 20 21 22 23 24
Saturday	00 01 02 03 04 05 06 07 08 09 10 11 12 13 14 15 16 17 18 19 20 21 22 23 24
Holiday	00 01 02 03 04 05 06 07 08 09 10 11 12 13 14 15 16 17 18 19 20 21 22 23 24

 Apply

This parameter helps you set time profiles within a week period. A profile is active when it matches the set intervals.


If a day is marked as holiday (refer to **Directory Holidays**), the last table row (Holiday) is applied regardless of the day in a week.

Make sure that the real time settings are correct (refer to the Date and Time subsection) to make this function work properly.

 Note

- *You can set any number of intervals within a day: 8:00-12:00, 13:00-17:00, 18:00-20:00, e.g.*
- *To make a profile active for the whole day, enter one day-covering interval: 00:00-24:00.*

5.2.3 Holidays



Here select the bank holidays (including Sundays). You can assign them different time intervals than to working days in their time profiles.


You can set holidays for the coming 10 years (click the year number at the top of the screen to select a year). A calendar is displayed for you to select/unselect a holiday. Fixed (annual) holidays are marked green and variable holidays (valid for the particular year only) are blue. Click a date once to select a fixed holiday, click twice to select a variable holiday and click for the third time to remove the holiday from the holiday list.

5.3 Hardware

Here is what you can find in this section

- 5.3.1 Switches
- 5.3.2 Door
- 5.3.3 Audio
- 5.3.4 Backlight
- 5.3.5 Card Reader
- 5.3.6 Digital Inputs
- 5.3.7 Extenders
- 5.3.8 Lift Control

5.3.1 Switches



Switches provide a very flexible and efficient control of such peripherals connected to the Access Unit as electric door locks, lighting, additional ringing signalling, and so on. **2N Access Unit** allows you to configure to 2 independent all-purpose switches.

A switch can be activated by:

- entering a valid code via the **2N Access Unit** numeric keypad,
- tapping a valid RFID card on the reader,
- a predefined delay after another switch activation,
- by a time profile *),
- receiving an HTTP command from another LAN device *),
- the Action.ActivateSwitch action via Automation *).

Switch activation can be blocked by an appropriately selected time profile if necessary.



Caution

- The options marked with *) require their respective active licences.

If a switch is active, you can:

- activate any logical output of the **2N Access Unit** (relay, power output).


- activate the output to which the 2N[®] IP Security Relay module is connected.
- send an HTTP command to another device.

The switch can work in the monostable or bistable mode. The switch is switched off after a timeout in the monostable mode and switched on with the first activation and off with the next activation in the bistable mode.

The switch signals its state by:

- a programmable beep.
- a LED indicator if available in the 2N Access Unit model.

List of Parameters



- **Switch Enabled** – enable/disable the switch globally. When disabled, the switch cannot be activated by any of the available codes (including user switch codes), by quick dial button.
- **Switch mode** – set the monostable/bistable mode for the switch. The switch is switched off after a timeout in the monostable mode and switched on with the first activation and off with the next activation in the bistable mode.
- **Switch-on duration** – set the switch-on time for a monostable switch. This value is not applied in the bistable mode.
- **Controlled output** – assign an electric output to the switch. Choose one of the available intercom outputs: relay, power output, extender output. If you select **None**, the switch will not control any electric output but can control external equipment via HTTP commands.

- **Output type** – if you use the 2N® IP Intercom - Security Relay module, set the output type to **Security**. In the **Security** mode, the output works in the inverse mode, i.e. remains closed and controls the 2N® IP Intercom - Security Relay module using a specific pulse sequence. If you use the inverse mode (i.e. the door is locked when voltage is applied), set the **inverse** output type.
- **Time profile** – assign a pre-defined time profile to the switch or set the switch activating time manually. If the time profile is inactive, the switch cannot be activated by a code, call or quick dial button.
- **"Test the switch" button** – activate the switch manually to test its function, e.g. an electric lock or another device connected.

Activation Codes ▾

	CODE	TIME PROFILE
1	00	☒ [not used] ▾ ☐
2		☒ [not used] ▾ ☐

Distinguish on/off codes ☐

The table above includes a list of universal codes that help you activate switches from 2N Access Unit keypad. Up to 10 universal codes can be defined for each switch (depending on the particular intercom model).

- **Code** – enter the numerical code for the switch. The code must include at least two door unlocking characters via the intercom keypad and at least one door unlocking character via DTMF. We recommend you to use four characters at least. Codes 00 and 11 cannot be entered and are not accepted from a numeric keypad; they are reserved for opening doors via DTMF. Confirm the code with *. The code length is up to 16 characters.
- **Time Profile** – assign a time profile to the switch code to control its validity.
- **Distinguish on/off codes** – Set a switch code mode in which odd codes (1, 3) are used for switch activation and even codes (2, 4 ...) are for switch deactivation. This mode can only be used if the switch is set to the bistable mode.

Extended Activation ▾

Activation by Time Profile
☒ [not used] ▾
☐

- **Activation by Time Profile** – activate the switch by a pre-defined time profile. The switch will remain active as long as the assigned time profile is active.

State Signalling ▾

Sound Signalling

Long beep ▾

- **Sound Signalling** – set the sound signalling type for switch activation. Choose the Short beep or Long beep (during the whole activation).

Synchronisation ▾

Synchronise with

[not used] ▾

Synchronisation Delay

10

[s]

- **Synchronise with** – set switch synchronisation to enable automatic switch activation after another switch activation with a predefined delay. Define the delay in the **Synchronisation Ddelay** parameter.
- **Synchronisation Delay** – set the time interval between synchronised activations of two switches. The parameter will not be applied unless the **Synchronise** function is enabled.

HTTP Commands ▾

Switch-On Command

Switch-Off Command

Username

Password

- **Switch-On Command** – set the command to be sent to the external device (WEB relay, e.g.) upon switch activation. The command is sent via the HTTP (GET request) and must be as follows: **http://ip_address/path**. E.g.: **http://192.168.1.50/relay1=on**.
- **Switch-Off Command** – set the command to be sent to the external device (WEB relay, e.g.) upon switch deactivation. The command is sent via the HTTP (GET request) and must be as follows: **http://ip_address/path**. E.g.: **http://192.168.1.50/relay1=off**.
- **Username** – enter the username for the external device (WEB relay, e.g.) authentication. The parameter is obligatory only if the external device requires authentication.
- **Password** – enter the external device (WEB relay, e.g.) authentication password. The parameter is obligatory only if the external device requires authentication.

 Tip

In case of use external relay **part no.: 9137410E** are used next HTTP commands:

To turn on the switch - `http://ip_address/state.xml?relayState=1` (e.g.: `http://192.168.1.10/state.xml?relayState=1`)

To turn on for pre-defined time (default value is 1.5 s) - `http://ip_address/state.xml?relayState=2` (e.g.: `http://192.168.1.10/state.xml?relayState=2`)

To turn off - `http://ip_address/state.xml?relayState=0` (e.g.: `http://192.168.1.10/state.xml?relayState=0`)


In case of use external relay **part no.: 9137411E** are used next HTTP commands (Symbol X should be replaced with a number of the desired switch):

To turn on the switch - `http://ip_address/state.xml?relayXState=1` (e.g.: `http://192.168.1.10/state.xml?relay1State=1`)

To turn on for pre-defined time (default value is 1.5 s) - `http://ip_address/state.xml?relayXState=2` (e.g.: `http://192.168.1.10/state.xml?relay1State=2`)

To turn off - `http://ip_address/state.xml?relayXState=0` (e.g.: `http://192.168.1.10/state.xml?relay1State=0`)

5.3.2 Door




List of Parameters

Door



- **Assigned switch** – select a switch for the electromagnetic door lock control. The switch state controls the door unlocking signalling (green door symbol, green LED).



- **Assigned input** – define one (or none) of the logical inputs for open door detection.

- **Input Mode** – set the active input mode (polarity). Non Inverted / Inverted.
- **Unauthorised door open detection** – detect if the door is open when switch has been locked.
- **Door open too long detection** – door open too long detection.
- **Maximum door open time** – maximum permitted door open duration in seconds.

REX Button ▾

Assigned Input

None ▾

Input Mode

Non Inverted ▾

- **Assigned input** – select one (or none) of the logic inputs for the departure button function. The departure button input activation activates the selected switch. The activation time and mode are set by the selected switch parameters.
- **Input mode** – set the active input mode (polarity).

Genetec Synergis ▾

Enabled ☐

Synergis Server Address

Username

Password

Connection State **DISCONNECTED**

Failure Reason -

- **Enabled** – enable connection with the Genetec Synergis external security system.
- **Synergis server address** - Synergis server IP address or domain name.
- **Username** – authentication user name.
- **Connection state** – display the current Synergis server connection state or error state description if necessary.
- **Failure reason** – display the failure reason of the last Synergis server connection attempt – the last error response, 404 Not Found, for example.

Entry Rules

☒ Access Enabled

- **Access enabled** – enable access in a direction (entry, exit). If access is disabled, the door cannot be opened from the selected side.

Emergency Lockdown ▾

Current State **OFF** 

- **Emergency Lockdown** – display the active door lock setting: Unlocked/Locked.



Caution

- Emergency lockdown is superior to all time and access profiles.

Access Profiles ▾

	TIME PROFILE	AUTHENTICATION MODE	ZONAL CODE
1	 [not used] ▾ 	Any Type Accepted ▾	☒
2	 [not used] ▾ 	Any Type Accepted ▾	☒
3	 [not used] ▾ 	Any Type Accepted ▾	☒
4	in other cases	Any Type Accepted ▾	☒

- **Time profile** – choose one or more time profiles to be applied. Set the time profiles in Directory / Time profiles
 - 
 - select one of the pre-defined profiles or set the time profile for the given element manually.
- **Authentication mode** – set the authentication mode for the time profile in this row including multiple authentication for enhanced security. Select Access denied to ban access.

- **Zonal code** – enable the zonal code for the time profile and authentication combination in this row. You can use the zonal code instead of the user PIN.

Caution

- If the time profile is unset, the authentication mode is ignored on the given row.

Advanced Settings ▾

Zonal Code

Authentication Signaling

LED + Audio ▾

Virtual Card to Wiegand

Do Not Forward ▾

Silent Alarm Enabled

☐

Limit Failed Access Attempts

☐

- **Zonal code** – enter the switch numeric zonal code consisting of two characters at least. However, four characters at least are recommended.
- **Authentication signalling** – select how to signal that a card or another identifier has been read. The options are LED only (light signalling) or LED + sound (light signalling), when the card has been read no matter if valid or invalid.
- **Virtual card to Wiegand** – select a group of Wiegand outputs to which the Virtual user card No. shall be sent after successful authentication. Can be combined with any authentication method, including codes, fingerprints, etc.
- **Silent alarm enabled** – a virtual code higher by 1 than the access code is assigned to each access code and used for silent alarm activation. For example, if the access code is 0000, then the silent alarm activation code is 0001. It means, for instance, that silent alarm is 0000 for access code 9999 and so on. Set the silent alarm action in the Automation section.
- **Limit failed access attempts** – enable the maximum count of unsuccessful authentication attempts. After five unsuccessful attempts (wrong numeric code, invalid card, etc.), the access module will be blocked for 30 seconds even if authentication is valid.

Service Cards ▾

Plus Card ID



Minus Card ID



Service cards are two common cards that are dedicated to this particular purpose by you. Be sure to complete their IDs in the Plus card ID and Minus card ID items in this section. The count of access card ID characters is given by the card type and is variable. However, it holds true that all cards of the same type have equally long IDs.

The plus/minus cards are used for user card administration. When a plus card is tapped on the card reader, any other tapped card is added to the Directory list as a new user with an access card assigned. The user !Visitor #card_ID is automatically created in the device. When a minus card is tapped on the card reader, any other tapped card and its user are deleted from the Directory list. The RFID card record will be cancelled and access via this card will be blocked.

- **Plus card ID** – enter the service card ID for adding cards to the Installed cards: a sequence of 6 to 32 characters including 0-9, A-F.
- **Minus card ID** – enter the service card ID for removing cards from the Installed cards: a sequence of 6 to 32 characters including 0-9, A-F.

Anti-Passback ▾

Mode

Off ▾

Time limitation

5 minutes ▾

Anti-Passback is a security function preventing users to use their access cards or other identifiers to re-enter an area without leaving it before (i.e. preventing users from sharing cards).

- **Mode** – enable/disable the Anti-Passback mode:
 - **Off** – the function is Off by default allowing the user to use the access card or another identifier to re-enter an area without leaving it before.
 - **Soft** – the user is allowed to use the access card or another identifier to re-enter an area without leaving it before. A new **AccessTaken** record is made in Status / Events.
 - **Hard** – the user is not allowed to use the access card or another identifier to re-enter an area without leaving it before. A new **UserRejected** record is made in Status / Events.
- **Time limitation** – select an Anti-Passback timeout during which the user cannot re-enter an area using the given authentication method (card, code, etc.) in the same direction.

Exit Rules

☒ Access Enabled

- **Access enabled** – enable access in a direction (entry, exit). If access is disabled, the door cannot be opened from the selected side.

Emergency Lockdown ▾

Current State **OFF** 

- **Emergency Lockdown** – display the active door lock setting: Unlocked/Locked.




Caution

- Emergency lockdown is superior to all time and access profiles.

Access Profiles ▾

	TIME PROFILE	AUTHENTICATION MODE	ZONAL CODE	REX BUTTON
1	 [not used] ▾ 	Any Type Accepted ▾	☒	☒
2	 [not used] ▾ 	Any Type Accepted ▾	☒	☒
3	 [not used] ▾ 	Any Type Accepted ▾	☒	☒
4	in other cases	Any Type Accepted ▾	☒	☒

- **Time profile** – choose one or more time profiles to be applied. Set the time profiles in Directory / Time profiles.



– select one of the pre-defined profiles or set the time profile for the given element manually.

- **Authentication mode** – set the authentication mode for the time profile in this row including multiple authentication for enhanced security. Select Access denied to ban access.

- **Zonal code** - enable the zonal code for the time profile and authentication combination in this row. You can use the zonal code instead of the user PIN.
- **REX button** - enable the exit button function for the selected time profile. Set the exit button input in Hardware / Door / Door tab.



Caution

- If the time profile is unset, the authentication mode is ignored on the given row.

Advanced Settings ▾

Zonal Code

Authentication Signaling

LED + Audio ▾

Virtual Card to Wiegand

Do Not Forward ▾

Silent Alarm Enabled

☐

Limit Failed Access Attempts

☐

- **Zonal code** - enter the switch numeric zonal code consisting of two characters at least. However, four characters at least are recommended.
- **Authentication signalling** - select how to signal that a card or another identifier has been read. The options are LED only (light signalling) or LED + sound (light signalling, when the card has been read no matter if valid or invalid).
- **Virtual card to Wiegand** - select a group of Wiegand outputs to which the Virtual user card No. shall be sent after successful authentication. Can be combined with any authentication method, including codes, fingerprints, etc.
- **Silent alarm enabled** - a virtual code higher by 1 than the access code is assigned to each access code and used for silent alarm activation. For example, if the access code is 0000, then the silent alarm activation code is 0001. It means, for instance, that silent alarm is 0000 for access code 9999 and so on. Set the silent alarm action in the Automation section.
- **Limit failed access attempts** - enable the maximum count of unsuccessful authentication attempts. After five unsuccessful attempts (wrong numeric code, invalid card, etc.), the access module will be blocked for 30 seconds even if authentication is valid.

Service Cards ▾

Plus Card ID



Minus Card ID



Service cards are two common cards that are dedicated to this particular purpose by you. Be sure to complete their IDs in the Plus card ID and Minus card ID items in this section. The count of access card ID characters is given by the card type and is variable. However, it holds true that all cards of the same type have equally long IDs.

The plus/minus cards are used for user card administration. When a plus card is tapped on the card reader, any other tapped card is added to the Directory list as a new user with an access card assigned. The user !Visitor #card_ID is automatically created in the device. When a minus card is tapped on the card reader, any other tapped card and its user are deleted from the Directory list. The RFID card record will be cancelled and access via this card will be blocked.

- **Plus card ID** – enter the service card ID for adding cards to the Installed cards: a sequence of 6 to 32 characters including 0-9, A-F.
- **Minus card ID** – enter the service card ID for removing cards from the Installed cards: a sequence of 6 to 32 characters including 0-9, A-F.

Anti-Passback ▾

Mode

Off ▾



Time limitation

5 minutes ▾

Anti-Passback is a security function preventing users to use their access cards or other identifiers to re-enter an area without leaving it before (i.e. preventing users from sharing cards).


- **Mode** – enable/disable the Anti-Passback mode:
 - **Off** – the function is Off by default allowing the user to use the access card or another identifier to re-enter an area without leaving it before.
 - **Soft** – the user is allowed to use the access card or another identifier to re-enter an area without leaving it before. A new **AccessTaken** record is made in Status / Events.
 - **Hard** – the user is not allowed to use the access card or another identifier to re-enter an area without leaving it before. A new **UserRejected** record is made in Status / Events.
- **Time limitation** – select an Anti-Passback timeout during which the user cannot re-enter an area using the given authentication method (card, code, etc.) in the same direction.

5.3.3 Audio



- **Key beep volume** – set the key beep volume. The volume values are relative against the set master volume.
- **Warning tone volume** – set the volume of warning and signalling tones described in the **Signalling of Operational Statuses** section. The volume values are relative against the set master volume.
- **Switch activation tone volume** – set the volume of the switch activation tone. The volume values are relative against the set master volume.

5.3.4 Backlight



Use this tab to set the module backlight and signalling LED brightness levels separately.



- **Backlight** – set the backlight brightness value for the day mode. Set the value as a percentage of the maximum possible LED brightness.




- **Signaling LEDs** – set the signaling LED brightness value for the day mode. Set the value as a percentage of the maximum possible LED brightness.

 Note

- The brightness parameters affect the function, power consumption and general appearance of your device. A high nametag and button backlight value may, if the ambient light level is low, dazzle the persons standing in front of the intercom and, in general, increase the power consumption of the device. A low LED brightness value, on the other hand, may, if the intercom is placed in direct sun, result in a lower LED on/off contrast and potential LED state identification problems.

5.3.5 Card Reader



Card Reader helps you control access to your building effectively using contactless RFID cards. The supported card types depend on the card reader model used.

List of Parameters

Basic Settings ▾

Door

Associated Switch


- **Door** – set the reader direction (Arrival, Departure) for the Attendance system purposes.
- **Associated Switch** – select a switch to be activated whenever a valid card is applied. The set value is not applied when a valid user card is tapped on the reader while the double authentication mode is enabled. In this case, a numeric switch activating code is required to identify the switch to be activated.

RFID Interface ▾

Allowed Card Types

Samsung NFC Compatibility ☐


- **RFID Interface** – choose the permitted types of cards (select/unselect).
- **Samsung NFC Compatibility** – allows for Samsung Smartphone NFC.



Caution

- Unlike earlier Access Unit versions, where card readers were displayed separately, the 2N[®] Access Unit 2.0 card readers are set in the Hardware / Extending modules section.

5.3.6 Digital Inputs



In this configuration section set the parameters associated with the digital inputs and their interconnections with other functions.

List of Parameters

Secured State Control ▾

Assigned Input

Input Mode

- **Assigned input** – define one (or none) of the logical inputs for secured state detection. The secured state is then signalled by a red LED on the **2N Access Unit**.
- **Input mode** – set the active level of the input (polarity).

Tamper Switch ▾

Assigned Input

Enable Automatic Switch Blocking ☐

Switch Blocking State **Not Blocked**

Unblock

The tamper switch equipped models help detect opening of the device cover and signal this event as **TamperSwitchActivated**. The events are written into a log and read out via HTTP API (refer to the **HTTP API** manual).

If the function is enabled, all the switches get blocked for 30 minutes whenever the tamper is activated. Blocking is active even after the device restart. Each port can be controlled via **Automation**. Press the **UNBLOCK** button, disable the function or reset the configuration factory values to unblock the switches.

- **Assigned input** – select the logical input to which the tamper switch is to be connected. **TamperSwitchActivated** signals the tamper switch activation.
- **Enable automatic switch blocking** – block the switches by tamper activation for 30 minutes.
- **Switch blocking state** – display and make switch blocking settings.

 Note


- From PCB version 599v2 up, each of the models is equipped with an optical tamper switch.
- From PCB version 599v2 up, the assigned input is indicated by a module pictogram backlight. In lower PCB versions, it is indicated by the LED light on the right-hand module side.

 Note

Menu Digital Inputs is available for models:

- 2N[®] IP Verso
- 2N[®] IP Vario and 2N[®] IP Force if an internal card reader is installed
- 2N Access Unit

5.3.7 Extenders



You can enhance the **2N Access Unit** with extending modules connected to the basic unit. The following modules are available:

- Keypad module
- Infopanel module
- Card reader module
- Bluetooth module
- I/O module
- Wiegand module
- Inductive loop module
- Display module
- Fingerprint reader
- Touch keypad
- Touch keypad & RFID reader 125 kHz, 13.56 MHz
- Bluetooth & RFID reader 125 kHz, 13.56 MHz

The modules are chain-like interconnected. Each of the modules has its number depending on the chain position (the first module has number 0).

You can configure each module separately. The parameters are specific for the given module type .

 Note

- *The modules can also be configured via the text row with a list of parameters (parameter_name=parameter_value) separated with semicolons. At present, just a few of these parameters are available. The other parameters are not public as they are rather experimental and can be modified in the future.*

 Note

- Module Name has to be unique.
- Unnameable modules can be addressed via ext <module_position>.

Keypad Module Configuration

1 - Keypad (54-0908-1932) ▾

Module Name

Door
Door Entry ▾

Forward to Wiegand Output
Do Not Forward ▾

Transmitted Code Format
Wiegand 8-bit ▾



Locate Module

- **Module Name** – set the module name for logging events from the keypad.
- **Door** – set the reader direction (Door Entry, Door Exit) for the Attendance system purposes.
- **Forward to Wiegand Output** – set a group of Wiegand outputs to which all pressed keys are to be forwarded.
- **Transmitted Code Format** – select a 4bit or 8bit (higher security) format for the codes to be transmitted.

Infopanel Module Configuration

6 - Info Panel (54-0957-0595) ▾



Locate Module

- No parameters are available to the public at present.

125 kHz Card Reader Module Configuration

1 - 125 kHz Card Reader (54-1411-0144) ▾

Module Name

Door

Door Entry ▾

Associated Switch

Door Lock Switch ▾

Allowed Card Types

EMarine, HID Prox, HID Prox, Rederia, t ▾

Forward to Wiegand Output

Group 1 ▾



Locate Module

- **Module Name** – set the module name for card reader logging purposes.
- **Door** – set the reader direction (Not specified, Arrival, Departure) for the Attendance system purposes.
- **Associated Switch** – set the switch to be activated after user authentication via this module. If you set Door Lock Switch, the authentication rules specified in Hardware / Door will be used.
- **Allowed Card Types** – set the type of a card to be accepted by the card reader. The card reader supports just one card type at an instant.

- **Forward to Wiegand Output** – set a group of Wiegand outputs to which all the received RFID card IDs will be resent.

✓ **Tip**

- To accelerate card reading, you are recommended to select the card types used by the user in the module settings.

13.56 MHz Card Reader Module Configuration

3 - 13.56 MHz Card Reader (54-1216-0005) ▾

Module Name

Door

Door Entry ▾

Associated Switch

Door Lock Switch ▾

Allowed Card Types

ISO14443A (Mifare), HID iClass CSN, H ▾

Samsung NFC Compatibility

No ▾

Forward to Wiegand Output

Group 1 ▾



Locate Module

- **Module Name** – set the module name for card reader logging purposes.
- **Door** – set the reader direction (Door Entry, Door Exit) for the Attendance system purposes.
- **Associated Switch** – set the switch to be activated after user authentication via this module. If you set Door Lock Switch, the authentication rules specified in Hardware / Door will be used.
- **Allowed Card Types** – set the type of a card to be accepted by the card reader. The card reader supports just one card type at an instant.
- **Samsung NFC Compatibility** – enable NFC compatibility with the Samsung phones.
- **Forward to Wiegand Output** – set a group of Wiegand outputs to which all the received RFID card IDs will be resen

✓ **Tip**

- To accelerate card reading, you are recommended to select the card types used by the user in the module settings.

Bluetooth Module

4 - Bluetooth (54-1761-0131) ▾

Module Name

Door
Door Entry ▾

Associated Switch
Door Lock Switch ▾

Signal Range
Short ▾

Operation Mode
Tap in app ▾



Locate Module

- **Module Name** – set the module name for logging events from the Bluetooth module.
- **Door** – set the reader direction (Not specified, Arrival, Departure) for the Attendance system purposes.
- **Associated Switch** – set the switch to be activated after user authentication via this module. If you set Door Lock Switch, the authentication rules specified in Hardware / Door will be used.
- **Signal Range** – set the maximum signal range, i.e. the distance within which the Bluetooth module can communicate with the mobile phone:
 - **Short** – less than 50 cm for most phones
 - **Middle** – less than 2 m for most phones
 - **Long** – maximum possible range

- **Operation Mode** – set the authentication method for a mobile phone:
 - **Tap in app** – authentication has to be confirmed by tapping on an icon in the application running in a mobile phone.
 - **Touch mode** – touch the card reader having a phone with paired 2N[®] Mobile Key to confirm authentication.

Warning

- An upgrade to version 2.30 is followed by upgrades in the Bluetooth modules. A downgrade to version 2.29 and lower may make the Bluetooth modules non-functional.

I/O Module Configuration

6 - I/O Module (54-0761-0164) ▾

Module Name

io1



- **Module Name** – set the module name for input/output specification in the SetOutput, GetInput and InputChanged objects in **Automation**.

Wiegand Module Configuration

The Wiegand module is equipped with the input and output Wiegand interfaces, which are mutually independent, have separate settings and can receive and send codes at the same time. The Wiegand input helps you connect such equipment as RFID card readers, biometric readers and so on. With the Wiegand output, you can connect the intercom to the security system in your building, for example (to send IDs of the RFID cards tapped on the RFID reader or codes received on any Wiegand input). The 2N[®] **Wiegand Isolator** is also equipped with one logical input and one logical output, which can be controlled via **Automation**.

3 - Wiegand Module (54-1846-0251) ▾

Module Name

Door

Door Entry ▾

Associated Switch

Door Lock Switch ▾

Received Code Format

Wiegand 26-bit, Wiegand 32-bit, Wiegand 37-bit ▾

Output Wiegand Group

Group 1 ▾

Transmitted Code Format

Wiegand 26-bit ▾

Change Facility Code

No ▾

Facility Code



- **Module Name** – set the module name for input/output specification in the SetOutput, GetInput and InputChanged objects in the **2N Automation**.
- **Door** – set the reader direction (Arrival, Departure) for the Attendance system purposes.
- **Associated Switch** – set the switch to be activated after user authentication via this module. If you set Door Lock Switch, the authentication rules specified in Hardware / Door will be used.
- **Received Code Format** – set the format for the codes to be received (Wiegand 26, 32, 37 and RAW).
- **Output Wiegand Group** – assign the output Wiegand to a group to which the codes from the connected card readers or Wiegand inputs can be resent.
- **Transmitted Code Format** – set the format for the codes to be transmitted (26-bit, 32-bit, 37-bit and RAW format, 35-bit, Corp. 1000, 48-bit, Corp. 1000 and Auto).
- **Change Facility Code** – set the first code part via Wiegand. This applies to Wiegand OUT for 26-bit code format. Contact your security system supplier to know if the Facility Code is requested.
- **Facility Code** – define the 2N IP device location in the security system. Enter a decimal value for the location (0-255).

Induction Loop Module Configuration

2 - Induction Loop Module (54-1132-0002) ▾

Maximum Power
 ▾



Locate Module

- **Maximum Power** – set the maximum transmission power for the induction loop antenna. A higher transmission power means a wider range, but less power for other intercom functions. The convenient default value is 0.25 W under normal circumstances.

Display Module Configuration

1 - Display (54-1264-0045) ▾



Locate Module

- **Module Name** – set the module name for input/output specification in the SetOutput, GetInput and InputChanged objects in the **2N Automation**.
- **Door** – set the reader direction (Arrival, Departure) for the Attendance system purposes.



Caution

- The display is not supported on Access Unit 1.0 from FW version 2.27.

Fingerprint Reader Module Configuration

0 - Fingerprint Scanner (54-1829-0266) ▼

Module Name

Door
Door Entry ▼

Associated Switch
Door Lock Switch ▼



Locate Module

- **Module Name** – set the module name for logging events from the Fingerprint reader.
- **Door** – set the reader direction (Arrival, Departure) for the Attendance system purposes.
- **Associated Switch** – set the switch to be activated after user authentication via this module. If you set Door Lock Switch, the authentication rules specified in Hardware / Door will be used.



Caution

- Whenever the fingerprint reader is disconnected, the User fingerprints will be hidden in the user profile after restart. This section displays how many user fingerprints have been uploaded to the intercom memory. Once a fingerprint reader is reconnected, the User fingerprints will be displayed again.

Touch Keypad

2 - Touch Keypad (54-1790-0012) ▾

Module Name

Door
 ▾

Blink at Keystroke
 ▾

Forward to Wiegand Output
 ▾

Transmitted Code Format
 ▾



- **Module Name** – set the module name for logging events from the keypad.
- **Door** – set the reader direction (Door Entry, Door Exit) for the Attendance system purposes.
- **Blink at Keystroke** – set keystroke light signalling for noisy environments where acoustic signals are difficult to hear.
- **Forward to Wiegand Output** – set a group of Wiegand outputs to which all pressed keys are to be forwarded.
- **Transmitted Code Format** – select a 4bit or 8bit (higher security) format for the codes to be transmitted.

Touch Keypad & RFID Reader 125 kHz, 13.56 MHz

1 - 13.56 MHz + 125 kHz Card Reader (54-2025-0074) ▾

Module Name

Door
Door Entry ▾

Associated Switch
Door Lock Switch ▾

Allowed Card Types
EMarine, HID Prox, HID Prox, Rederia, t ▾

Samsung NFC Compatibility
No ▾

Forward to Wiegand Output
Group 1 ▾



Locate Module

2 - Touch Keypad (54-2025-0074) ▾

Module Name

Door
Door Entry ▾

Blink at Keystroke
No ▾

Forward to Wiegand Output
Do Not Forward ▾

Transmitted Code Format
Wiegand 8-bit ▾



Locate Module

13.56 MHz (125 kHz) Card Reader (serial number)

- **Module Name** – set the module name for card reader logging purposes.
- **Door** – set the reader direction (Not specified, Arrival, Departure) for the Attendance system purposes.

- **Associated Switch** – set the switch to be activated after user authentication via this module. If you set Door Lock Switch, the authentication rules specified in Hardware / Door will be used.
- **Allowed Card Types** – set the type of a card to be accepted by the card reader. The card reader supports just one card type at an instant.
- **Samsung NFC Compatibility** – enable NFC compatibility with the Samsung phones.
- **Forward to Wiegand Output** – set a group of Wiegand outputs to which all the received RFID card IDs will be resent.

Touch keypad (serial number)

- **Module Name** – set the module name for logging events from the touch keypad module.
- **Door** – set the reader direction (Door Entry, Door Exit) for the Attendance system purposes.
- **Blink at Keystroke** – set keystroke light signalling for noisy environments where acoustic signals are difficult to hear.
- **Forward to Wiegand Output** – set a group of Wiegand outputs to which all pressed keys are to be forwarded.
- **Transmitted Code Format** – select a 4bit or 8bit (higher security) format for the codes to be transmitted.

Bluetooth & RFID Reader 125 kHz, 13.56 MHz

1 - 13.56 MHz + 125 kHz Card Reader (54-2029-0016) ▾

Module Name

Door
Door Entry ▾

Associated Switch
Door Lock Switch ▾

Allowed Card Types
ISO14443A (Mifare), HID iClass CSN, 21 ▾

Samsung NFC Compatibility
No ▾

Forward to Wiegand Output
Group 1 ▾



Locate Module

2 - Bluetooth (54-2029-0016) ▾

Module Name

Door
Door Entry ▾

Associated Switch
Door Lock Switch ▾

Signal Range
Middle ▾

Operation Mode
Tap in app ▾



Locate Module

13.56 MHz (125 kHz) Card Reader (serial number)

- **Module Name** – set the module name for card reader logging purposes.
- **Door** – set the reader direction (Not specified, Arrival, Departure) for the Attendance system purposes.

- **Associated Switch** – set the switch to be activated after user authentication via this module. If you set Door Lock Switch, the authentication rules specified in Hardware / Door will be used.
- **Allowed Card Types** – set the type of a card to be accepted by the card reader. The card reader supports just one card type at an instant.
- **Samsung NFC Compatibility** – enable NFC compatibility with the Samsung phones.
- **Forward to Wiegand Output** – set a group of Wiegand outputs to which all the received RFID card IDs will be resent.

Bluetooth (serial number)


- **Module Name** – set the module name for logging events from the Bluetooth module.
- **Door** – set the reader direction (Not specified, Arrival, Departure) for the Attendance system purposes.
- **Associated Switch** – set the switch to be activated after user authentication via this module. If you set Door Lock Switch, the authentication rules specified in Hardware / Door will be used.
- **Signal Range** – set the maximum signal range, i.e. the distance within which the Bluetooth module can communicate with the mobile phone:
 - **Short** – less than 50 cm for most phones
 - **Middle** – less than 2 m for most phones
 - **Long** – maximum possible range
- **Operation Mode** – set the authentication method for a mobile phone:
 - **Tap in app** – authentication has to be confirmed by tapping on an icon in the application running in a mobile phone.
 - **Touch mode** – touch the card reader having a phone with paired 2N[®] Mobile Key to confirm authentication.



Caution

- Be sure to configure the replaced modules. The configuration is tied with the module serial number.

5.3.8 Lift Control



To control the floor lift access, connect the AXIS A9188 relay module to the **2N Access Unit**. Up to 5 relay modules can be connected to one **2N Access Unit**, each of which can control up to 8 floors, which makes a total of 40. Make sure that the [2N Access Unit Lift module license](#) is active (Part No. [9160401](#)) to make this function work.

Relay Modules

Basic Settings ▾

Switch-On Duration [s]

- **Switch-On Duration** – set the relay module activation time (range of 1 – 600 s).

Relay modules (AXIS A9188) ▾

	ENABLED	IP ADDRESS	STATE	SERIAL NUMBER
io_1	☐	192.168.0.90	Offline	
io_2	☐	192.168.0.90	Offline	
io_3	☐	192.168.0.90	Offline	
io_4	☐	192.168.0.90	Offline	
io_5	☐	192.168.0.90	Offline	

- **Enabled** – activate/deactivate the AXIS A9188 module used for lift control for up to 8 floors.
- **IP address** – AXIS A9188 IP address.
- **State** – display the state of the connected AXIS A9188 module (Error/Access denied/Ready/Offline).
- **Serial number** – AXIS A9188 serial number.

Authentication ▾

Username

Password

- **Username** – external device authentication username. The parameter is only mandatory if the external device requests authentication.
- **Password** – external device (WEB relay, etc.) authentication password. The parameter is only mandatory if the external device requests authentication.



Caution

- You just need one authentication username and password for all the modules.

Floors

Floors ▾

	FLOOR NAME	PUBLIC ACCESS	PROFILE
io_1_1	R&D	☒	☒ [not used] ▾ ☐ 
io_1_2	IT	☒	☒ [not used] ▾ ☐ 
io_1_3	Buffet	☒	☒ [not used] ▾ ☐ 
io_1_4		☐	☒ [not used] ▾ ☐ 
io_1_5		☐	☒ [not used] ▾ ☐ 
io_1_6		☐	☒ [not used] ▾ ☐ 
io_1_7		☐	☒ [not used] ▾ ☐ 

- Floor name** – set the floor name.
- Public access** – activate permanent floor access without any authentication.
- Profile** – select one or more time profiles to be applied. Set the time profiles in the Directory / Time Profiles section.



mark the selection from predefined profiles or manual setting of a time profile for the given element.



set a time profile for the given element.

 Tip**Certificate generation for AXIS A9188**


1. Retrieve the AXIS A9188 relay module in the LAN using **AXIS IP Utility** .
2. Enter the root/root login.
3. Select Preferences / Additional device configuration in the menu.
4. A new device configuration window gets displayed.
5. Select System Options / Security / Certificates.
6. Click Create self-signed certificate to create a certificate.
7. Complete all the required fields and click OK for confirmation.
8. Go to System Options / Security / HTTPS.
9. Select the certificate in a pop-up menu and press Save to save it.
10. Move to the **2N Access Unit** web interface, Hardware / Lift Control. Enter the login data and the relay module IP address.
11. READY gets displayed at the relay module if the connection has been successful.

5.4 Services

Here is what you can find in this section:

- 5.4.1 E-mail
- 5.4.2 Mobile Key
- 5.4.3 Automation
- 5.4.4 HTTP API
- 5.4.5 Web Server
- 5.4.6 SNMP

5.4.1 E-mail



To inform the intercom users on all missed and/or successfully completed calls, configure **2N IP intercom** to send an e-mail after every call to the called user. You can compile the e-mail subject and message text of your own. If your intercom is equipped with a camera, you can automatically attach one or more snapshots taken during the call or ringing.

The intercom sends e-mails to all the users whose valid e-mail addresses are included in the users list. If the **E-mail** parameter in the user list is empty, e-mails are sent to the default e-mail address.

You can also send e-mails via Automation using the **Action.SendEmail** action.

Note

- *The E-mail function is available with the Gold or Enhanced Integration licence only.*

List of Parameters

SMTP

- ☒ SMTP Service Enabled

- **SMTP service enabled** – enable/disable sending e-mails from the intercom.

SMTP Server Settings ▾

Server Address

Server Port

- **Server address** – set the SMTP server address to which e-mails shall be sent.
- **Server port** – specify the SMTP server port. Modify the value only if the SMTP server setting is substandard. The typical SMTP port value is 25.

SMTP Server Login ▾

Username

Password

User Certificate

Self Signed ▾

- **Username** – enter a valid username for login if the SMTP server requires authentication, or leave the field empty if not.
- **Password** – enter the SMTP server login password.
- **User certificate** – specify the user certificate and private key for the intercom – SMTP server communication encryption. Choose one of the three sets of user certificates and private keys (refer to the Certificates subs.) or keep the **Self Signed** setting, in which the certificate automatically generated upon the first intercom power up is used.

Common Email Settings ▾

From Address

- **From address** – set the sender address for all outgoing e-mails from the device.

Advanced Settings ▾

Deliver In

20 minutes ▾

- **Deliver In** – set the time limit for delivering an e-mail to an inaccessible SMTP server.



The image shows a software window titled "E-Mail Sending Diagnostics". It features a large, empty rectangular area with a light gray background and a vertical scrollbar on the right side. Below this area, there is a label "Test E-Mail Address" followed by a text input field. To the right of the input field is a button labeled "Apply & Test".

Click **Apply & Test** to send a testing e-mail to the defined address with the aim to test the functionality of the current e-mail sending setting. Enter the destination e-mail address into the Test e-mail address field and press the button. The current e-mail sending state is continuously displayed in the window for you to detect an e-mail setting problem if any on the intercom or another network element.

E-mail on Access

Set that an e-mail shall be sent whenever an RFID card is tapped on the card reader and/or Bluetooth/fingerprint reader identification is made.

E-Mail Sending Settings ▾

Send E-Mail at Denied Events ▾

Send E-Mail at – set e-mail sending. The following options are available:

- **Do Not Send E-mail** – no e-mail message will be sent.
- **All Accesses** – an e-mail will be sent at all (valid/invalid) access attempts.
- **Denied Accesses** – an e-mail will only be sent if the access is denied.

E-Mail Template ▾

Default To

Subject

Body

\$AuthIdType\$ event

<h1> Hello, \$User\$ </h1>

<h2> You had a \$AuthIdType\$ event at: \$DateTime\$ </h2>

<p>

<h2> The Authorisation ID is \$AuthId\$ and is \$AuthIdValid\$ </h2>

<p>

 This mail is generated automatically by the \$HeliosId\$ device. Do not reply to this please.

- **Default to** – the intercom sends messages to the e-mail address specified for the user when a valid user card is applied. When an invalid card is applied or no e-mail address is assigned to the user, the message shall be sent the e-mail address included here. If the receiver is included neither in the phone book nor in this parameter, no e-mail shall be sent. You can set more e-mail addresses separated with a comma if necessary.
- **Subject** – set the e-mail subject to be sent.
- **Body** – edit the text to be sent. Use the HTML formatting marks in the text. You can insert special symbols substituting the username, date and time, intercom /card identification, Bluetooth/fingerprint identifier and identifier validity for information. These symbols will be replaced with the actual value before sending. See the list of placeholders below:

2N TELEKOMUNIKACE a.s., www.2n.cz

85/131

1.
 - a. \$User\$ Called username
 - b. \$DateTime\$ Current date and time
 - c. \$AuthId\$ User authentication ID
 - d. \$DeviceName\$ Intercom identification
 - e. \$AuthIdType\$ Authentication type - define the identifier source (Card, Bluetooth or Fingerprint)
 - f. \$AuthIdValid\$ Identifier validity - valid for a valid identifier, Invalid for an invalid identifier

An extended syntax can be used for the \$AuthIdType\$ and \$AuthIdValid\$ placeholders to replace the values in different languages.

If the placeholder value is not found in the string, the value is used directly.

E-Mail on Event

Set that an e-mail shall be sent whenever the SIP gets lost, the device is rebooted or the tamper switch is activated on the device.

Settings ▾

Send E-mail at

Send to E-Mail Address

Device Rebooted

☒

Tamper Switch Activation

☒

Send to E-Mail Address - set e-mail sending. The following options are available:

- Device Rebooted
- Tamper Switch Activation

Device Restart Message ▾

Subject	Device Rebooted
E-Mail Body	<pre><h1>Hello,</h1>
 <h2>Device rebooted: \$DateTime\$</h2> This mail is generated automatically by the \$DeviceName\$ device. Do not reply to this please. </pre>

Device Restart Message – set the message to be sent to the specified e-mail address whenever the device is restarted.

- **Subject** – set the e-mail subject to be sent.
- **E-mail Body** – edit the text to be sent. Use the HTML formatting marks in the text. You can insert special symbols substituting the username, date & time and device ID. These symbols will be replaced with the actual value before sending. Refer to the table of substitute symbols below:

1. \$User\$ Called username
2. \$DateTime\$ Current date and time
3. \$DeviceName\$ Intercom identification

If the placeholder value is not found in the string, the value is used directly.

Tamper Activated Message ▾

Subject	Tamper Switch Activated
E-Mail Body	<pre><h1> Hello, </h1>
 <h2> Tamper Switch Activated: \$DateTime\$ </h2> This mail is generated automatically by the \$DeviceName\$ device. Do not reply to this please. </pre>


Tamper Activated Message - set the message to be sent to the specified e-mail address whenever the tamper switch is activated.

- **Subject** - set the e-mail subject to be sent.
- **E-mail Body** - edit the text to be sent. Use the HTML formatting marks in the text. You can insert special symbols substituting the username, date & time and device ID. These symbols will be replaced with the actual value before sending. Refer to the table of substitute symbols below:

1. \$User\$ Called username
2. \$DateTime\$ Current date and time
3. \$DeviceName\$ Intercom identification

If the placeholder value is not found in the string, the value is used directly.

5.4.2 Mobile Key



The **2N Access Unit** equipped with the Bluetooth module allow for user authentication via the **2N[®] Mobile Key** application available to devices with iOS 8.1 and higher (iPhone 4 s and higher phones) or Android 4.4 KitKat and higher (Bluetooth 4.0 Smart supporting phones).

User Identification (Auth ID)

The 2N[®] Mobile Key application authenticates itself with a unique identifier on the 2N Access Unit side: Auth ID (128-bit number) is generated randomly for every user and paired with the 2N Access Unit user and its mobile device.

Note

- The generated Auth ID cannot be saved in more mobile devices than one. This means that Auth ID uniquely identifies just one mobile device or its user.

You can set and edit the Auth ID value for each user in the Mobile Key section of the 2N Access Unit phone book. You can move Auth ID to another user or copy it to another intercom. By deleting the Auth ID value you can block the user's access.

Encryption Keys and Locations

The 2N[®] Mobile Key – 2N Access Unit communication is always encrypted. 2N[®] Mobile Key cannot authenticate a user without knowing the encryption key. The primary encryption key is automatically generated upon the 2N Access Unit first launch and can be re-generated manually any time later. Together with AuthID, the primary encryption key is transmitted to the mobile device for pairing.

You can export/import the encryption keys and location identifier to other 2N Access Unit. 2N Access Units with identical location names and encryption keys form so-called **locations**. In one location, a mobile device is paired just once and identifies itself with one unique Auth ID (i.e. a user AuthID can be copied from one 2N Access Unit to another within a location).

Pairing

Pairing means transmission of user access data to a user personal mobile device. The user access data can only be saved into one mobile device, i.e. a user cannot have two mobile devices for authentication, for example. However, the user access data can be saved into multiple locations in one mobile device (i.e. the mobile device is used as a key for more locations at the same time).

The following data is transmitted to a mobile device for pairing:

- U s e r A u t h I D

An encryption key other than that used for communication after pairing is used in the pairing mode for security reasons. This key is generated automatically upon the **2N Access Unit** first launch and can be re-generated any time later.

The **2N Access Unit** can keep up to 4 valid encryption keys: 1 primary and up to 3 secondary ones. A mobile device can use any of the 4 keys for communication encryption. The encryption keys are fully controlled by the system administrator. It is recommended that the encryption keys should be periodically updated for security reasons, especially in the event of a mobile device loss or intercom configuration leak.

- The encryption keys are generated automatically upon the **2N Access Unit** first launch and saved into the **2N Access Unit** configuration file. We recommend you to re-generate the encryption keys manually before the first use to enhance security.

When a key is deleted, the **2N[®] Mobile Key** users that still use this key will not be able to authenticate themselves unless they have updated the encryption keys in their mobile devices before deletion. The mobile device keys are updated at every use of the **2N[®] Mobile Key** application.

List of Parameters

Location ID

Export/Import

- **Location ID** – set a unique identifier for the location in which the selected encryption key set is valid.
- **Export** – push the button to export the location ID and current encryption keys into a file. Subsequently, the exported file can be imported to another device. Devices with identical location IDs and encryption keys form a so-called location.
- **Import** – push the button to import the location ID and current encryption keys from a file exported from another **2N Access Unit**. Devices with identical location IDs and encryption keys form a so-called location.

Encryption Keys for Location

	KEY ID	CREATION TIME	
1	3EF7181130203B7A	05/08/2016 10:38:06	↺ x
2			x
3			x
4			x

- **Restore primary key** – by generating a new primary encryption key you delete the oldest secondary key. Thus, the **2N[®] Mobile Key** users that still use this key will not be able to authenticate themselves unless they have updated the encryption keys in their mobile devices before deletion. The mobile device keys are updated at every use of the **2N[®] Mobile Key** application.
- **Delete primary key** – delete the primary key to prevent the users that still use this key from authentication.
- **Delete secondary key** – the **2N[®] Mobile Key** users that still use this key will not be able to authenticate themselves unless they have updated the encryption keys in their mobile devices before deletion. The mobile device keys are updated at every use of the **2N[®] Mobile Key** application.

Pairing Mode Settings ▾

Pairing PIN Validity 1 hour ▾

Encryption Key for Pairing

	KEY ID	CREATION TIME	
1	D9268E4F32008638	05/08/2016 10:26:43	

- **Pairing PIN validity** – set the authorisation PIN validity for user mobile device pairing with the **2N Access Unit** .

 Tip

- In the case of loss of a mobile phone with access data proceed as follows:
 1. Delete the Mobile Key Auth ID value for the user to block the lost phone and avoid misuse.
 2. Re-generate the primary encryption key (optionally) to avoid misuse of the encryption key stored in the mobile device.

 Warnung

- With the upgrade to version 2.30, the bluetooth modules will also be upgraded. When downgrading to version 2.29 and lower, they may malfunction.

5.4.3 Automation

←

Services

⚙️

📊

👤

🔧

⚙️

📱

E-Mail

Mobile Key 

Automation >

HTTP API

Web Server

SNMP

2N Access Unit 2.0

CZ | EN | DE | FR | IT | ES | RU

Log out


Functions ▾

ENABLED	NAME	STATUS	ACTIONS
☒	Function1	Empty	 
☒	Function2	Empty	 
☒	Function3	Empty	 
☒	Function4	Empty	 
☒	Function5	Empty	 

The **2N Access Unit** provides highly flexible setting options to satisfy variable user needs. There are situations in which the standard configuration settings (switch or call modes, e.g.) are insufficient and so **2N Access Unit** offers a special programmable interface, **2N Automation**. Typically, **2N Automation** is used in applications that require complex interconnections with third party systems.

Refer to the **2N Automation** Configuration Manual for the **2N IP Automation** function and configuration details.

5.4.4 HTTP API



2N HTTP API is an application interface designed for control of selected **2N IP intercom** functions via the **HTTP**. It enables **2N IP intercoms** to be integrated easily with third party products, such as home automation, security and monitoring systems, etc.

2N HTTP API provides the following services:

- **System API** – provides intercom configuration changes, status info and upgrade.
- **Switch API** – provides switch status control and monitoring, e.g. door lock opening, etc.
- **I/O API** – provides intercom logic input/output control and monitoring.
- **Audio API** – provides configuration of audio signalling.
- **Logging API** – Logging API

Set the transport protocol (**HTTP** or **HTTPS**) and way of authentication (**None**, **Basic** or **Digest**) for each function. Create up to five user accounts (with own username and password) in the **HTTP API** configuration for detailed access control of services and functions.

Refer to the **2N HTTP API Configuration Manual** for the HTTP API function and configuration details.

☒ Account Enabled

User Settings ▾

User Name
 Password

User Privileges ▾

DESCRIPTION	MONITORING	CONTROL
System Access	☒	☒
I/O Access	☐	☐
Switch Access		☐
Audio Access		☒
UID (Cards & Wiegand) Access	☐	
Keyboard access	☐	

5.4.5 Web Server



You can configure your **2N Access Unit** using a standard browser with access to the integrated web server. Use the secured HTTPS protocol for communication between the browser and **2N Access Unit**. Having accessed the intercom, enter the login name and password. The default login name and password are **admin** and **2n** respectively. We recommend you to change the default password as soon as possible.

The Web Server function is used by the following **2N Access Unit** functions too:

1. HTTP commands for switch control, refer to the Switches subsection.
2. Event.HttpTrigger in **2N Automation**; refer to the respective manual.

The unsecured HTTP protocol can be used for these special communication cases.

List of Parameters



- **Device Name**– set the device name to be displayed in the right upper corner of the web interface, login window and other applications if available (**2N® IP Manager**, **2N® IP Network Scanner**, etc).
- **Web Interface Language** – set the default language for administration web server login. Use the upper toolbar buttons to change the language temporarily.
- **Password** – set the intercom access password. Press  to change the password. The 8-character password must include one lower-case letter, one upper-case letter and one digit at least.

Advanced Settings ▾

HTTP Port	80
HTTPS Port	443
Minimum Allowed TLS Version	TLS 1.0
HTTPS User Certificate	Self Signed
Remote Access Enabled	☒

- **HTTP port** – set the web server port for HTTP communication. The port setting will not be applied until the intercom gets restarted.
- **HTTPS port** – set the web server port for HTTPS communication. The port setting will not be applied until the intercom gets restarted.
- **Minimum Allowed TLS Version** – define the lowest TLS version to be connected to the devices.
- **HTTPS user certificate** – specify the user certificate and private key for the intercom HTTP server – user web browser communication encryption. Choose one of the three sets of user certificates and private keys (refer to the Certificates subsection) or keep the **SelfSigned** setting, in which the certificate automatically generated upon the first intercom power up is used.
- **Remote access enabled** – enable remote access to the intercom web server from off-LAN IP addresses.

User Localization ▾

FILE	SIZE	
Original Language	130 kB	
User Language	N/A	  

- **Original Language** – download the original file containing all the user interface texts in English. The file format is XML; see below.
- **User Language** – record, load and remove, if necessary, a user file containing your own user interface text translations.

```
<?xml version="1.0" encoding="UTF-8"?>
<strings language="English" languageshort="EN">
  <!-- Global enums-->
  <s id="enum/error/1">Invalid value!</s>
  <s id="enum/bool_yesno/0">NO</s>
  <s id="enum/bool_yesno/1">YES</s>
  <s id="enum/bool_user_state/0">ACTIVE</s>
  <s id="enum/bool_user_state/1">INACTIVE</s>
  <s id="enum/bool_profile_state/0">ACTIVE</s>
  <s id="enum/bool_profile_state/1">INACTIVE</s>
  ..
  ..
  ..
</strings>
```

While translating, modify the value of **<s>** elements only. Do not modify the **id** values. The language name specified by the **language** attribute of the **<strings>** element will be available in the selections of the Web interface language parameter. The abbreviation of the language name specified by the **languageshort** attribute of the **<strings>** element will be included in the language list in the right-hand upper corner of the window and will be used for a quick language switching.

5.4.6 SNMP



The 2N Access Unit integrate a remote intercom supervision functionality via the SNMP. The 2N Access Unit support the SNMP version 2c.

List of Parameters

☒ SNMP Enabled

- **SNMP Enabled** – Allows you to enable the SNMP function

SNMP Settings ▾

Community String

Trap IP Address

Download MIB File

- **Community String** – text string representing the access key to the MIB table objects.
- **Trap IP Address** – IP address to which the SNMP traps are to be sent.
- **Download MIB File** – download the current MIB definition from a device.

SNMP Identification ▾

Contact

Name

Location

- **Contact** – enter the device manager contact (name, e-mail, etc.).
- **Name** – enter the device name.

- **Location** – enter the device location (1st floor, e.g.).

Authorised IP Addresses ▾

IP Address 1


- **IP Address** – enter up to 4 valid IP addresses for SNMP agent access to block access from other addresses. If the field is empty, the device may be accessed from any IP address.

5.5 System

Here is what you can find in this section:

- 5.5.1 Network
- 5.5.2 Date and Time
- 5.5.3 Licence
- 5.5.4 Certificates
- 5.5.5 Auto Provisioning
- 5.5.6 Syslog
- 5.5.7 Maintenance

5.5.1 Network



As the **2N Access Unit** is connected to the LAN, make sure that its IP address has been set correctly or obtained from the LAN DHCP server. Configure the IP address and DHCP in the Network subsection.

Tip

- To know the current IP address of your **2N Access Unit**, use the **2N IP Network Scanner**, which can be freely downloaded from www.2n.cz, or apply the steps described in the Installation Manual of the respective **2N Access Unit**: the **2N Access Unit** communicates its IP address to you via a voice function.

If you use the RADIUS server and 802.1x-based verification of connected equipment, you can make the intercom use the EAP-MD5 or EAP-TLS authentication. Set this function on the 802.1x tab.

The Trace tab helps you launch capture of incoming and outgoing packets on the **2N Access Unit** network interface. The file with captured packets can be downloaded for Wireshark processing, e.g. (www.wireshark.org).

List of Parameters

☒ Use DHCP Server

- **Use DHCP Server** – enable automatic obtaining of the IP address from the LAN DHCP server. If the DHCP server is unavailable or inaccessible in your LAN, use the manual network settings.

Manual Settings ▾

Static IP Address	192.168.1.100
Network Mask	255.255.255.0
Default Gateway	192.168.1.1
Primary DNS	
Secondary DNS	

- **Static IP Address** – display the static IP address of the **2N Access Unit**, which is used together with the below mentioned parameters if the Use DHCP Server parameter is disabled.
- **Network Mask** – set the network mask.
- **Default Gateway** – set the address of the default gateway, which provides communication with off-LAN equipment.
- **Primary DNS** – set the primary DNS server address for translation of domain names to IP addresses. The primary DNS value is 8.8.8.8 upon factory reset.
- **Secondary DNS** – set the secondary DNS server address, which is used in case the primary DNS is inaccessible. The secondary DNS value is 8.8.4.4 upon factory reset.

Network Identification ▾

Hostname	2NAccessUnit-5411050190
Vendor Class Identifier	

- **Hostname** – set the 2N IP intercom network identification.
- **Vendor Class Identifier** – set the vendor class identifier as a string of characters for DHCP Option 60.

VLAN Settings ▾

VLAN Enabled	☐
VLAN ID	1

- **VLAN Enabled** – enable the virtual network (VLAN) support (according to recommendation 802.1q). Set the virtual network ID too to make the function work properly.
- **VLAN ID** – select a virtual network ID in the range of 1-4094. The device shall receive only the packets tagged with this ID. A wrong setting may result in a connection loss and need to reset the device to factory values.

LAN Port Settings ▾

Required Port Mode Autonegotiation ▾
Current Port State **Full Duplex - 100mbps**

- **Required Port Mode** – set the preferred network interface port mode: Autonegotiation or Half Duplex – 10 mbps. The lower bit rate of 10 mbps may be necessary if the used network infrastructure (cabling) is not reliable for the 100mbps traffic.
- **Current Port State** – current network interface port state (Half or Full Duplex – 10 mbps or 100 mbps).

Tools ▾

Verify the network address accessibility Ping

- **Verify the network address accessibility** – verify the network address accessibility via the Ping command in standard operating systems. Press Ping to display a dialogue, enter the IP address/domain name and click Ping to send test data to this address. If the selected IP address/domain name is invalid, a warning is displayed and Ping remains inactive until the given IP address becomes valid. The function progress and result are also displayed in the dialogue. Failed means either inaccessibility of the given IP address within 10 seconds or inability to translate the domain name into an address. If a valid response is received, the IP address from which the response came and the response waiting time in milliseconds are displayed. Repress Ping to send another query to the same address.

802.1x

The tab is not displayed for 2N Access Unit 2.0, which does not support the 802.1x protocol.

Device Identity ▾

Device Identity

- **Device Identity** – set the user name (identity) for authentication via EAP-MD5 and EAP-TLS.

MD5 Authentication ▾

MD5 Authentication Enabled
☐

Password

- **MD5 Authentication Enabled** – enable authentication of network devices via the 802.1x EAP-MD5 protocol. Do not enable this function if your LAN does not support 802.1x. If you do so, the **2N Access Unit** will become inaccessible.
- **Password** – enter the access password for EAP-MD5 authentication.

TLS Authentication ▾

TLS Authentication Enabled
☐

Trusted Certificate

None ▾

User Certificate

None ▾

- **TLS Authentication Enabled** – enable authentication of network devices via the 802.1x EAP-TLS protocol. Do not enable this function if your LAN does not support 802.1x. If you do so, the **2N Access Unit** will become inaccessible.
- **Trusted Certificate** – specify the set of trusted certificates for verification of the RADIUS server public certificate validity. Choose one of three sets of certificates; refer to the Certificates subsection. If no trusted certificate is included, the RADIUS public certificate is not verified.
- **User Certificate** – specify the user certificate and private key for verification of the **2N Access Unit** authorisation to communicate via the 802.1x-secured network element port in the LAN. Choose one of three sets of user certificates and private keys; refer to the Certificates subsection.

Trace

On the Trace tab, you can launch capturing of incoming and outgoing packets on the **2N Access Unit** network interface. The captured packets are stored in a 4 MB buffer. When the buffer fills up, the oldest packets are overwritten automatically. We recommend you to lower the video stream transmission rate below 512 kbps while capturing. Press  to start,  to stop and  to download the packet capture file.

Packet Capture Status ▾

Current State **RUNNING**


Buffer Size **1 MB**

Buffer Utilization **1 MB**

Number of Captured Packets **4501**

Packet Capture Control   

5.5.2 Date and Time



If you control validity of lock activation codes and similar by time profiles, make sure that the **2N Access Unit** internal date and time are set correctly.

2N Access Unit is equipped with a back-up real-time clock to withstand up to several days' long power outages. You can synchronise the **2N Access Unit** time with your PC anytime by pressing the **Synchronise** button.

Note

- *The **2N Access Unit** does not need the current date and time values for its basic function. However, be sure to set these values when you apply time profiles and display time of listed events (Syslog, used cards, logs downloaded by **2N IP intercom** HTTP API, etc.).*

Practically, the **2N Access Unit** real-time circuit accuracy is approximately $\pm 0,005$ %, which may mean a deviation of ± 2 minutes per month. Therefore, we recommend you to synchronise time with the NTP server to achieve the highest accuracy and reliability. The **2N Access Unit** sends a query to the NTP server periodically to update its time value.

List of Parameters

Current Time ▾

Current Device Time **04/03/2015 09:09:52**

Synchronise with browser

Synchronise – push the button to synchronise the **2N Access Unit** time value with your PC time value.

Time Zone ▾

Time Zone (UTC+01:00) Europe/Paris ▾

Time Zone Rule

- **Time Zone** – set the time zone for the installation site to define time shifts and winter/summer time transitions.
- **Time Zone Rule** – if the **2N Access Unit** is installed on a site that it not included in the Time zone parameter, set the time zone rule manually. The rule is applied only if the Time zone parameter is set to **Manual** (specify time shifts and winter/summer time transitions manually).

NTP Server ▾


Use NTP Server ☒

NTP Server Address time.nist.gov

NTP Time Status **Not synchronized**

- **Use NTP Server** – enable the NTP server use for **2N Access Unit** time synchronisation.
- **NTP Server Address** – set the IP address/domain name of the NTP server used for your **2N Access Unit** time synchronisation.

5.5.3 Licence



Some 2N Access Unit functions are available with a valid licence key only. Refer to the **Function Licensing** subsection for the list of 2N Access Unit licensing options.

List of Parameters

Licence Settings ▾

Serial Number	54-0984-0032
Licence Key	
Licence Key Valid	NO

- **Serial Number** – display the serial number of the device for which the licence is valid.
- **Licence Key** – enter the valid licence key.
- **Licence Key Valid** – check whether the used licence key is valid.

License Status ▾

Enhanced Security **YES**

Enhanced Integration **YES**

NFC Support **YES**

Lift Control Support **YES**

- **Enhanced Security** – check whether the functions activated by the Enhanced Security licence are available.
- **Enhanced Intergration** – check whether the functions activated by the Enhanced Integration licence are available.
- **NFC Support** – check whether the functions activated.
- **Lift Control Support** – check whether the functions activated by the Lift Module license are available.

Online licence download ▾

Automatic Update ☒

Manual Update

Manual Update State -

- **Automatic update** – enable automatic license key update from the 2N License server.
- **Manual update** – manual license availability check request.
- **Manual update state** – running, updated, unspecified, failed: license is not available.


Trial Licence ▾

Trial Licence State **Expired**

Licence Expiry **0 hours**

- **Trial Licence State** – check the trial licence state (Non-Activated, Activated, Expired).
- **Licence Expiry** – display the remaining time of the trial licence validity.

5.5.4 Certificates



Some **2N Access Unit** network services use the Transaction Layer Security (TLS) protocol for communication with other LAN devices to prevent third parties from monitoring and/or modifying the communication contents. Unilateral or bilateral authentication based on certificates and private keys is needed for establishing connections via TLS.

The following **2N Access Unit** services use the TLS protocol:

1.
 - a. Web server (HTTPS)
 - b. E-mail (SMTP)
 - c. 802.1x (EAP-TLS)
 - d. SIPs

The **2N Access Unit** intercoms allow you to load up to three sets of trusted certificates, which help authenticate LAN devices for communication with the **2N Access Unit**, plus three sets of user certificates and private keys for communication encryption.

Each certificate-requiring service can be assigned one of the three certificate sets available; refer to the **Web Server**, **E-Mail** and **Streaming** subsections. The certificates can be shared by the services.

2N Access Unit accepts the DER (ASN1) and PEM certificate formats.

Upon the first power up, the **2N Access Unit** automatically generates the **Self Signed certificate** and **private key** for the **Web server** and **E-mail** services without forcing you to load a certificate and private key of your own.

Note

- If you use the Self Signed certificate for encryption of the intercom web server – browser communication, the communication is secure, but the browser will warn you that it is unable to verify the **2N Access Unit** certificate validity.

Refer to the tables below for the current list of trusted and user certificates:

Trusted Certificates ▾			
CA IDENTITY	ISSUER	EXPIRY TIME	
(1)			 
(2)			 
(3)			 


User Certificates ▾			
CA IDENTITY	ISSUER	EXPIRY TIME	
(1)			 
(2)			 
(3)			 

Press  to load a certificate saved on your PC. Select the certificate (or private key) file in the dialogue window and push **Load**. Press  to remove a certificate from the intercom.

Caution

- For certificates based on elliptic curves use the secp256r1 (aka prime256v1 aka NIST P-256) and secp384r1 (aka NIST P-384) curves only.

5.5.5 Auto Provisioning



The **2N Access Unit** allows you to update firmware and configuration manually or automatically from a storage on a TFTP/HTTP server selected by you according to predefined rules.

You can configure the TFTP and HTTP server address manually. The **2N Access Unit** supports automatic address identification via the local DHCP server (Option 66).

Firmware

Use the Firmware tab to set automatic firmware download from a server defined by you. The **2N Access Unit** compares the server file with its current firmware file periodically and, if the server file is more recent, automatically updates firmware and gets restarted (approx. 30 s). Hence, we recommend you to update when the **2N Access Unit** traffic is very low (at night, e.g.).

The **2N Access Unit** expects the following files:

1. MODEL-firmware.bin – **2N Access Unit** firmware
2. MODEL-common.xml – common configuration for all **2N Access Unit**
3. MODEL-MACADDR.xml –specific configuration for one **2N Access Unit**

MODEL in the filename specifies the intercom model:

1. au – 2N Access Unit
2. aug2 – 2N Access Unit 2.0

MACADDR is the MAC address of the **2N Access Unit** in the 00-00-00-00-00-00 format. Find the MAC address on the **2N Access Unit** production plate or on the **Status** tab in the web interface.

Example:

2N Access Unit with MAC address 00-87-12-AA-00-11 downloads the following files from the TFTP server:

- au-firmware.bin
- au-common.xml
- au-00-87-12-aa-00-11.xml

List of Parameters

☒ Firmware Update Enabled

- **Firmware/Configuration Update Enabled** – enable automatic firmware /configuration updating from the TFTP/HTTP server.

Server Settings ▾

Address Retrieval Mode DHCP (Option 66/150) ▾

Server Address

DHCP (Option 66/150) Address tftp://10.0.25.41

File Path /

Use Authentication ☒

Username

Password

Trusted Certificate Not used ▾

User Certificate

- **Address Retrieval Mode** – select whether the TFTP/HTTP server address shall be entered manually or a value retrieved automatically from the DHCP server using Option 66 shall be used.

- **Server Address** - enter the TFTP (tftp://ip_address), HTTP (http://ip_address) or HTTPS (https://ip_address) server address manually.
- **DHCP (Option 66/150) Address** - check the server address retrieved via the DHCP Option 66 or 150.
- **File Path** - set the firmware/configuration filename directory or prefix on the server. The intercom expects the XhipY_firmware.bin, XhipY-common.xml and XhipY-MACADDR.xml files, where X is the prefix specified herein and Y specifies the intercom model.
- **Use Authentication** - enable authentication for HTTP server access.
- **Username** - enter the user name for server authentication.
- **Password** - enter the password for server authentication.
- **Trusted Certificate** - set the set of CA certificates for validation of the ACS public certificate.
- **User Certificate** - specify the user certificate and private key to validate the intercom right to communicate with the ACS.

Update Schedule ▾

At Boot Time	Check for Update ▾
Update Period	Daily ▾
Update At	01:00
Next Update At	04/04/2015 01:00:00
Apply & Update	

- **At Boot Time** - enable check and/or execution of update upon every **2N Access Unit** start.
- **Update Period** - set the update period. Set an automatic update to take place hourly/daily/weekly/monthly, or set the period manually.
- **Update At** - set the update time in the HH:MM format for periodical updating at a low-traffic time. The parameter is not applied if the update period is set to a value shorter than 1 day.
- **Next Update At** - display the next update time.

Update Status ▾

Last Update At	12/15/2015 01:00:00
Update Result	Server Not Found

- **Last Update At** - display the last update time.

Update Result - display the last update result. The following options are available:

Result	Description
In progress ...	Update in progress
Updated	The configuration/firmware update has been successful. With firmware update, the device will be restarted in a few seconds.
Firmware is up to date.	The firmware update attempt reveals that the latest firmware version has been loaded.
DHCP Option 66 has failed.	The server address loading via DHCP Option 66 or 150 has failed.
Invalid domain name	The server domain name is invalid due to wrong configuration or unavailability of the DNS server.
Server Not Found	The requested HTTP/TFTP server fails to reply.
Download failed	An unspecified error occurred during file download.
File not found	The file has not been found on the server.
File invalid	The file to be downloaded is corrupted or of a wrong type.

Configuration

Use the Configuration tab to set automatic configuration download from the server defined by you. The **2N Access Unit** periodically downloads a file from the server and gets reconfigured without getting restarted.

☒ Automatic Configuration Update

- **Firmware update enabled** – enable automatic firmware/configuration updating from the TFTP/HTTP server.

Server Settings ▾

Address Retrieval Mode DHCP (Option 66/150) ▾

Server Address

DHCP (Option 66/150) Address **tftp://10.0.25.41**

File Path

Use Authentication ☒

Username

Password

Trusted Certificate Not used ▾

User Certificate

- **Address Retrieval Mode** – select whether the TFTP/HTTP server address shall be entered manually or a value retrieved automatically from the DHCP server using Option 66 shall be used.
- **Server Address** – enter the TFTP (**tftp://ip_address**), HTTP (**http://ip_address**) or HTTPS (**https://ip_address**) server address manually.
- **DHCP (Option 66/150) Address** – check the server address retrieved via the DHCP Option 66 or 150.
- **File Path** – set the firmware/configuration filename directory or prefix on the server. The intercom expects the XhipY_firmware.bin, XhipY-common.xml and XhipY-MACADDR.xml files, where X is the prefix specified herein and Y specifies the intercom model.
- **Use Authentication** – enable authentication for HTTP server access.
- **Username** – enter the user name for server authentication.
- **Password** – enter the password for server authentication.
- **Trusted Certificate** – set the set of CA certificates for validation of the ACS public certificate.
- **User Certificate** – specify the user certificate and private key to validate the intercom right to communicate with the ACS.

Info

- The intercom contains the Factory Cert, a signed certificate used for British Telecom integration, for example.

Update Schedule ▾

At Boot Time

Update Period

Update At

Next Update At **Disabled**

Update Now

- **At Boot Time** – enable check and, if possible, update execution upon every intercom start.
- **Update Period** – set the update period. Set an automatic update to take place hourly/daily/weekly/monthly, or set the period manually.
- **Update At** – set the update time in the HH:MM format for periodical updating at a low-traffic time. The parameter is not applied if the update period is set to a value shorter than 1 day.
- **Next Update At** – set the next update time.

Update Status ▾

Last Update At **09/06/2019 01:30:20**

Update Result (Common Config) **DHCP option 66 failed**

Communication Result Detail (Common configuration) **N/A**

Update Result (Private Config) **DHCP option 66 failed**

Communication Result Detail (Private configuration) **N/A**

- **Last Update At** – last update time .
- **Update Result (Common Config)** – last update result. The following options are available: DHCP option 66 failed, Firmware is up to date, Server connection failed, Running..., File not found.
- **Communication Result Detail (Common Config)** – server communication error code or TFTP/HTTP status code.
- **Update Result (Private Config)** – private configuration follows the common configuration update. The device with private configuration is identified by its MAC address. The following options are available: DHCP option 66 failed, Firmware is up to date, Server connection failed, Running..., File not found.
- **Communication Result Detail (Private Config)** – server communication error code or TFTP/HTTP status code.

My2N / TR069

Use this tab to enable and configure remote intercom management via the TR-069 protocol. TR-069 helps you reliably configure intercom parameters, update and back up configuration and/or upgrade device firmware.

The TR-069 protocol is utilised by the My2N cloud service. Make sure that TR-069 is enabled and Active profile set to My2N to make your intercom log in to My2N periodically for configuration.

This function helps you connect the intercom to your ACS (Auto Configuration Server). In this case, the connection to My2N will be disabled in the intercom.

☒ My2N / TR069 Enabled

- **My2N / TR069 Enabled** – enable connection to My2N or another ACS server.

General Settings ▾

Active Profile My2N ▾

Next synchronisation in **10h 59m 45s**

Connection Status **Synchronised**

Communication Status Detail **HTTP status: 204, No Content.**

Connection test

- **Active Profile** – select one of the pre-defined profiles (ACS), or choose a setting of your own and configure the ACS connection manually.
- **Next Synchronisation in** – display the time period in which the intercom shall contact a remote ACS.
- **Connection Status** – display the current ACS connection state or error state description if necessary.
- **Communication Status Detail** – server communication error code or HTTP status code.
- **Connection test** – test the TR069 connection according to the set profile, see the Active profile. The test result is displayed in the Connection status.

My2N Settings ▾

My2N ID

My2N Security Code **FSQA-RPXW-ZUXV-QOA7**

- **My2N ID** – unique identifier of the company created via the My2N portal.


- **My2N Security Code** – display the full application activating code.

Custom Server Settings ▾

ACS Server Address		i
Username		i
Password		i
Trusted Certificate	None ▾	
User Certificate	Self Signed ▾	
Periodic Inform Enabled	☒	i
Periodic Inform Interval		i


- **ACS server address** – set the ACS address in the following format: ipaddress[:port], 192.168.1.1:7547, for example.
- **Username** – set the user name for intercom authentication while connecting to the ACS server.
- **Password** – set the user password for intercom authentication while connecting to the ACS server.
- **Trusted certificate** – set the set of CA certificates for validation of the ACS public certificate. Choose one of three sets, see the Certificates subsection. If none is selected, the ACS public certificate is not validated.
- **User certificate** – specify the user certificate and private key to validate the intercom right to communicate with the ACS. Choose one of three sets, refer to the Certificates subsection.
- **Periodic inform enabled** – enable periodical logging of the intercom to the ACS.
- **Periodic inform interval** – set the interval of periodical logging of the intercom to the ACS if enabled by the Periodic inform enabled parameter.

5.5.6 Syslog



The **2N Access Unit** allow you to send system messages to the Syslog server including relevant information on the device states and processes for recording, analysis and audit. It is unnecessary to configure this service for common **2N Access Unit** operation.

List of Parameters



The screenshot shows the 'Syslog Server Settings' configuration form. It includes a checkbox for 'Send Syslog Messages' which is checked, a text input field for 'Server Address', and a dropdown menu for 'Severity Level' currently set to 'Info'.

- **Send Syslog Messages** - enable sending of system messages to the Syslog server. Make sure that the server address is set correctly.
- **Server Address** - set the IP/MAC address of the server on which the Syslog application is running.
- **Severity Level** - set the severity level of the messages to be sent. Debug 1-3 level setting is only recommended to facilitate troubleshooting for the Technical Support department.

Local Syslog Messages ▾

Saving Syslog Messages **RUNNING**

Syslog Messages Saving Passed Time **0h 4m 26s**

Syslog Messages Saving Remaining Time **0h 55m 34s**

Saved Syslog Messages Size **78,335 B**

Available Syslog Messages Saving Time **0h 4m 26s**


Available Syslog Messages Size **78,335 B**

Required Saving Time

Syslog Messages Saving Control    

General overview of local syslog messages.

5.5.7 Maintenance



Use this menu to maintain your **2N Access Unit** configuration and firmware. You can back up and reset all parameters, update firmware and/or reset default settings here.



- **Restore Configuration** – reset configuration from the preceding backup. Press the button to display a dialogue window for you to select and upload the configuration file to the **2N Access Unit**. You can also choose before uploading whether the directory, network parameters or SIP exchange connection settings from the configuration file shall be applied.
- **Backup Configuration** – back up the complete current configuration of your **2N Access Unit**. Press the button to download the configuration file to your PC.

Caution

- *Treat the file cautiously as the **2N Access Unit** configuration may include delicate information such as user phone numbers and access codes.*

- **Reset Configuration** – reset default values for all of the **2N Access Unit** parameters except for the network settings. Use the respective jumper or push **Reset** to reset all the **2N Access Unit** parameters; refer to the Installation Manual of your intercom.



Caution

- *The default state reset deletes the license key if any. Hence, we recommend you to copy it to another storage for later use.*

System ▾

Firmware Version **2.23.0.32.2**
 Bootloader Version **2.8.0.17.1**
 Software Build Type **beta**
 Software Build Date and Time **2/20/2018 16:52:32 PM**
 Upgrade Device Firmware **Upgrade Firmware**
 Firmware Status **Server error**
Check Now
 Notify of Beta Versions ☐
 Restart Device **Restart Device**
 Licences **Show**

- **Upgrade Firmware** – upgrade your **2N Access Unit** firmware. Press the button to display a dialogue window for you to select and upload the firmware file to the intercom. The **2N Access Unit** will automatically get restarted and new FW will then be available. The whole upgrading process takes less than one minute. Refer to www.2n.cz for the latest FW version for your intercom. FW upgrade does not affect configuration as the **2N Access Unit** checks the FW file to prevent upload of a wrong or corrupted file.
- **Check Firmware Online** – check online whether a new firmware version is available. If so, download the new FW version and an automatic device upgrade will follow.
- **Restart Device** – restart the **2N Access Unit**. The process takes about 30 s. When the **2N Access Unit** has obtained the IP address upon restart, the login window will get displayed automatically.



Caution

- The **2N Access Unit** configuration change writing takes 3-15 s depending on the **2N Access Unit** configuration size. Do not restart the intercom during this process.

- **License** - click Display to display a dialogue window including a list of used licenses and third party software as well as a EULA link.

Usage Statistics ▾

Send anonymous statistics data ☒

- **Send anonymous statistics data** - enable sending of anonymous statistic data on device usage to the manufacturer. These data do not include any sensitive information such as passwords, access codes or phone numbers. This information helps 2N TELEKOMUNIKACE a.s. improve the software quality, reliability and performance. Your participation is voluntary and you can cancel this sending any time.

6. Supplementary Information

Here is what you can find in this section:

- 6.1 Troubleshooting
- 6.2 Directives, Laws and Regulations
- 6.3 General Instructions and Cautions

6.1 Troubleshooting



For the most frequently asked questions refer to **faq.2n.cz**.

6.2 Directives, Laws and Regulations

2N Access Unit conforms to the following directives and regulations:

- 2014/53/EU for radio equipment
- 2011/65/EU on the restriction of the use of certain hazardous substances in electrical and electronic equipment
- 2012/19/EU on waste electrical and electronic equipment

Industry Canada

This Class A digital apparatus complies with Canadian ICES-003/NMB-003.

FCC

This equipment has been tested and found to comply with the limits for a Class A digital device, pursuant to part 15 of the FCC Rules.

NOTE: These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications.

However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna
- Increase the separation between the equipment and receiver
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected
- Consult the dealer or an experienced radio/TV technician for help

Changes or modifications to this unit not expressly approved by the party responsible for compliance could void the user's authority to operate this equipment.

6.3 General Instructions and Cautions

Please read this User Manual carefully before using the product. Follow all instructions and recommendations included herein.

Any use of the product that is in contradiction with the instructions provided herein may result in malfunction, damage or destruction of the product.

The manufacturer shall not be liable and responsible for any damage incurred as a result of a use of the product other than that included herein, namely undue application and disobedience of the recommendations and warnings in contradiction herewith.

Any use or connection of the product other than those included herein shall be considered undue and the manufacturer shall not be liable for any consequences arisen as a result of such misconduct.

Moreover, the manufacturer shall not be liable for any damage or destruction of the product incurred as a result of misplacement, incompetent installation and/or undue operation and use of the product in contradiction herewith.

The manufacturer assumes no responsibility for any malfunction, damage or destruction of the product caused by incompetent replacement of parts or due to the use of reproduction parts or components.

The manufacturer shall not be liable and responsible for any loss or damage incurred as a result of a natural disaster or any other unfavourable natural condition.

The manufacturer shall not be held liable for any damage of the product arising during the shipping thereof.

The manufacturer shall not make any warrant with regard to data loss or damage.

The manufacturer shall not be liable and responsible for any direct or indirect damage incurred as a result of a use of the product in contradiction herewith or a failure of the product due to a use in contradiction herewith.

All applicable legal regulations concerning the product installation and use as well as provisions of technical standards on electric installations have to be obeyed. The manufacturer shall not be liable and responsible for damage or destruction of the product or damage incurred by the consumer in case the product is used and handled contrary to the said regulations and provisions.

The consumer shall, at its own expense, obtain software protection of the product. The manufacturer shall not be held liable and responsible for any damage incurred as a result of the use of deficient or substandard security software.

The consumer shall, without delay, change the access password for the product after installation. The manufacturer shall not be held liable or responsible for any damage incurred by the consumer in connection with the use of the original password.

The manufacturer also assumes no responsibility for additional costs incurred by the consumer as a result of making calls using a line with an increased tariff.

Electric Waste and Used Battery Pack Handling



Do not place used electric devices and battery packs into municipal waste containers. An undue disposal thereof might impair the environment!

Deliver your expired electric appliances and battery packs removed from them to dedicated dumpsites or containers or give them back to the dealer or manufacturer for environmental-friendly disposal. The dealer or manufacturer shall take the product back free of charge and without requiring another purchase. Make sure that the devices to be disposed of are complete.

Do not throw battery packs into fire. Battery packs may not be taken into parts or short-circuited either.



An Axis company

2N TELEKOMUNIKACE a.s.

Modřanská 621, 143 01 Prague 4, Czech Republic

Phone: +420 261 301 500, Fax: +420 261 301 599

E-mail: sales@2n.cz

Web: www.2n.cz

v2.30